

# **12d**Model

## **Installing the Release Version of 12d Model 15 and 12d Network CodeMeters**

### **For 12d Model 15 C1f**

**August 2022**

**12d Solutions Pty LTd**

ACN 101 351 991

PO Box 351 Narrabeen NSW Australia 2101

Australia Telephone (02) 9970 7117 Fax (02) 9970 7118

International Telephone 61 2 9970 7117 Fax 61 2 9970 7118

email [support@12d.com](mailto:support@12d.com) web page [www.12d.com](http://www.12d.com)

## Disclaimer

*12d Model* is supplied without any express or implied warranties whatsoever.

No warranty of fitness for a particular purpose is offered.

No liabilities in respect of engineering details and quantities produced by *12d Model* are accepted.

Every effort has been taken to ensure that the advice given in this manual and the program *12d Model* is correct, however, no warranty is expressed or implied by *12d Solutions Pty Ltd*.

## Copyright

This manual is copyrighted and all rights reserved.

This manual may not, in whole or part, be copied or reproduced without the prior consent in writing from *12d Solutions Pty Ltd*.

Copies of *12d Model* software must not be released to any party, or used for bureau applications without the written permission of *12d Solutions Pty Ltd*.

Copyright (c) 1989-2022 by 12d Solutions Pty Ltd  
Sydney, New South Wales, Australia.

ACN 101 351 991

All rights reserved.

# Table of Contents

<b>A Guide to the Notes.....</b>	<b>5</b>
<b>Installing 12d Model 15 Release Version.....</b>	<b>6</b>
Requirements for Installing & Running 12d Model 15 .....	6
12d Model 15 is only 64 bit .....	6
Quick or Detailed Installation Notes.....	6
<b>Quick Installation Notes for 12d Model 15 .....</b>	<b>7</b>
Installing and Uninstalling .....	7
Hardware Locks (Dongles) Supported.....	7
12d Model Installs for Windows 10.....	8
CodeMeter Drivers.....	8
Certifying CodeMeters.....	8
For Users with 12d Model 14 Installed.....	9
Setting Up Your User Folder for 12d Model 15.....	9
Setting Up Your User_Lib Folder for 12d Model 15 .....	9
Setting Up Your env.4d File for 12d Model 15.....	9
Are You Using a 12d Network Lock? .....	10
Network CodeMeters .....	10
Using a 12d Network CodeMeter for the First Time.....	10
Updating Licenses in a Network CodeMeter.....	10
Documentation and What's New .....	11
<b>Detailed Notes for Installing 12d Model.....</b>	<b>12</b>
Folders Created by the Installation .....	26
Icons Created by the Installation.....	28
Copying Existing User, User_Lib and env.4d .....	28
End of the Notes for Installing 12d Model 15.....	29
<b>Certifying CodeMeters.....</b>	<b>30</b>
Certifying CodeMeters from 12d Model.....	30
Automatically Certifying CodeMeters from 12d Model.....	32
Certifying CodeMeters Using Control Center .....	33
Installing the CodeMeter Drivers Separately.....	35
<b>Documentation.....</b>	<b>40</b>
12d Model Reference Manual .....	40
Getting Started for Design Manual .....	42
Getting Started for Surveying Manual .....	44
12d Model Programming Language Manual .....	46
12d Field File Format.....	47
12dxml File Format.....	47
12da File Format .....	48
<b>What's New in 12d Model 15.....</b>	<b>49</b>
What's New pdf.....	49
What's New Summary of Additions Sorted by Sub-Version .....	49
What's New Summary of Fixed Bugs Sorted by Sub-Version .....	49
What's New Summary of All Additions up to V15C1f.....	50
What's New Summary of All Fixed Bugs up to V15 C1f.....	50
<b>Errors Installing and Authorising .....</b>	<b>51</b>
12d Model XX Not Authorising .....	51
Licence Expiry Warning .....	52
Dongle Missing .....	53
<b>Network CodeMeters .....</b>	<b>55</b>
Definitions and Guide to the Network Notes.....	57
Installing CodeMeter Drivers.....	59
Setting up a 12d Network CodeMeter.....	62

dongles.4d and nodes.4d .....	69
Updating dongles.4d .....	69
Updating nodes.4d .....	77
<b>CodeMeter Control Center &amp; WebAdmin .....</b>	<b>80</b>
Stopping & Starting the CodeMeter Runtime Server .....	81
CodeMeter Runtime Server - Control Centre .....	82
CodeMeter Runtime Server - WebAdmin .....	85
Port Address for CodeMeter Communication .....	87
Port Address - WebAdmin 6 .....	87
Port Address - WebAdmin 5 .....	88
Certifying CodeMeters .....	89
Certifying CodeMeters Using WebAdmin .....	90
Time Servers for Certified Time .....	96
Monitoring and Cancelling Licenses .....	98
Getting Info on CodeMeters on a Particular Server - WebAdmin 6 .....	99
Monitoring and Cancelling Licenses - WebAdmin 6 .....	101
Getting Info on CodeMeters on a Particular Server - WebAdmin 5 .....	106
Monitoring and Cancelling Licenses - WebAdmin 5 .....	108
Updating Licenses in Network CodeMeters .....	112
Generating the Context File (.WibuCmRac) .....	113
Errors Updating the Network CodeMeter .....	119
Replacing an Existing Network CodeMeter .....	120
End of the Notes on Network CodeMeters .....	120
Which Version of WebAdmin? .....	121

# 1 A Guide to the Notes

These notes contain the information for:

(a) Installing the release version of **12d Model**




**12d Model** needs to be installed on each computer it is going to run on.

For notes on installing **12d Model** for the first time, or on a computer that is already running **12d Model**, go to [2 Installing 12d Model 15 Release Version on page 6](#)

(b) Setting up a Network CodeMeter

By default when **12d Model** is installed it is set up for users with a **Local (single user or stand alone) CodeMeter** that only allows **12d Model** to be run on the computer with the Local CodeMeter attached to it. With a Local CodeMeter, if **12d Model** is to be run on another computer with that Local CodeMeter then the Local CodeMeter must be **moved** to the new computer. And **12d Model** will stop running on the computer that no longer has the Local CodeMeter attached to it.

To allow **12d Model** to run on a number of computers without having to move a CodeMeter to different computers, a **NETWORK CodeMeter** is used.

12d Local CodeMeter also referred to as a Single User or Standalone CodeMeter		12d Network CodeMeter
<b>Stubby USB</b>		<b>Silver USB</b>
with end cap and ring	without end cap and ring	
		
<b>Note:</b> the end cap and ring are cosmetic only		

For notes on setting up a **Network CodeMeter**, go to [9 Network CodeMeters on page 55](#)

## 2 Installing 12d Model 15 Release Version

### 2.1 Requirements for Installing & Running 12d Model 15

Before Installing and running **12d Model 15**, you need the following:

- (a) You must have **Administrator** privileges to install **12d Model**
- (a) Approximately 2 Gigabytes of disc space is required for the installation to succeed.
- (b) A **12d Model CodeMeter** or **Wibu** Lock for your computer
  - If **12d Model 15** is already running on your computer, the **CodeMeter** (or **Wibu**) lock you already have will work with the new version of **12d Model 15** once you have a *nodes* file for **12d Model 15**.
  - If **12d Model** has **NOT** been running on your computer then **DO NOT ATTACH THE LOCK TO YOUR COMPUTER** until after the CodeMeter/Wibu drivers have been installed as part of the installation procedure.
- (c) An email with the **12d Model 15** authorization file **nodes.12d15n** attached, or a folder with the **12d Model 15** authorization file **nodes.12d15n** or **nodes.4d** in it.
- (d) This document which has the internet links to the required executables and files
- (e) Access to the internet to download the required executables and files

Please check that you have all the above items before commencing the installation.

Also note that:

- (a) **12d Model 15** will **not install** on Windows XP or Windows Vista.
- (b) **12d Model 15** will not run with the **Hardlock** locks which were used for **12d Model 10** and earlier versions.
  - If you have a **12d Hardlock** lock, please contact your **12d Model Reseller** to obtain a replacement **CodeMeter** lock.
- (c) **12d Field** will only run with **CodeMeter** locks
  - If you are running **12d Field** and have a **12d Wibu** or **12d Hardlock** lock, please contact your **12d Model Reseller** to obtain a replacement **CodeMeter**.
- (d) A three-button mouse is essential to efficiently use **12d Model** on the desktop.

### 2.2 12d Model 15 is only 64 bit

Microsoft has a 64 bit Windows and an older 32 bit Windows operating system but **12d Model 15** is only being released for 64-bit Windows.

### 2.3 Quick or Detailed Installation Notes

For abbreviated instructions and links for Installing the Release Version of **12d Model**, go to [3 Quick Installation Notes for 12d Model 15 on page 7](#).

For detailed instructions and links for Installing the Release Version of **12d Model**, go to [4 Detailed Notes for Installing 12d Model on page 12](#).

## 3 Quick Installation Notes for 12d Model 15

This chapter contains abbreviated notes for installing **12d Model 15**, and the links to download all the files required for the installation.

For more detailed notes on installing **12d Model**, see [4 Detailed Notes for Installing 12d Model on page 12](#).

**Important Note: 12d Model 15 will not install on Windows XP or Vista.**

### 3.1 Installing and Uninstalling

- (a) You need to be Administrator to install **12d Model 15** and **CodeMeter** and/or **Wibu** drivers
- (b) **12d Model 15** is **64-bit only** - there is no 32-bit version.
- (c) You can have earlier versions of **12d Model**, both 64-bit and a 32-bit, on your computer at the same time as **12d Model 15**.
- (d) If **12d Model 15** is already installed on your computer then it will be replaced.

The **12d Model 15 Installer** checks for an existing matching **12d Model 15** and if one exists, it displays the version number and asks *if you want to Uninstall it*.

If you say **No** then the **12d Model 15** Install will terminate, leaving the existing **12d Model 15**.

#### Important Note

The **Uninstaller** deletes everything in the **Program Files\12d\12dmodel\15.00** folder so **do not modify** any of those files as they will be deleted by any future installs of **12d Model 15**.

Any modification that you make to these files must go into **User** or **User\_Lib**.

- (e) The Uninstaller will not delete any of the training material loaded into the folders **12d\15.0\training** and **12d\15.0\courses**.

The **12d Model 15 Installer** will overwrite any files of the same name in those folders.

- (f) **Do not attach the CodeMeter or Wibu locks before installing the drivers**

The **12d CodeMeter** or **12d Wibu** locks (dongles) must **NOT be attached** to the computer before the CodeMeter/Wibu drivers are installed (see [3.4 CodeMeter Drivers on page 8](#)).

### 3.2 Hardware Locks (Dongles) Supported

- (a) The brand **Hardlock** locks **can not** be used for **12d Model 15**.
- (b) **12d Field** is only available in **12d Model 15** for **CodeMeters**.
- (c) **Network CodeMeters** only support **12d Model 11** and above.
- (d) The older **Wibu** locks (non-CodeMeter) are supported for **12d Model 15** but are being phased out.

## 3.3 12d Model Installs for Windows 10

*The 12d Model Install for 64 bit Window 10 - approximately 1 Gb*

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12d\\_Model\\_15\\_C1f\\_64\\_Setup.exe](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12d_Model_15_C1f_64_Setup.exe)

## 3.4 CodeMeter Drivers

If you are using a **CodeMeter** for the first time on this computer, then you will need to install the **CodeMeter** drivers and this can be done as part of the **12d Model** installation.

If you want to install the **CodeMeter** drivers separately, they can be installed with:

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/CodeMeterRuntime\\_7\\_30a.exe](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/CodeMeterRuntime_7_30a.exe)

For the notes for installing the CodeMeter Drivers separately, see [5.4 Installing the CodeMeter Drivers Separately on page 35](#).

## 3.5 Certifying CodeMeters

A **CodeMeter** needs to be Certified **over the Internet** every two months. So you need to have access to the Internet for the first time you start up **12d Model** with a **CodeMeter** and then at least every two months.

Once **12d Model** is installed, there is an environment variable **AUTO\_CERTIFY\_DONGLE\_4D** that can set so that **12d Model** automatically certifies the **CodeMeter** when required.

See [5 Certifying CodeMeters on page 30](#).

Please contact your **12d Model Reseller** if you have any problems Certifying CodeMeters.



## 3.6 For Users with 12d Model 14 Installed

### 3.6.1 Setting Up Your User Folder for 12d Model 15

The folder **User** contains the files that you have modified to replace those that **12d Model** installs in the folder **Set\_ups**. For example, your own *names.4d* or *linestyl.4d*.

So if you have files in your **User** folder in **12d Model 14**, you will probably also want to use many of them with **12d Model 15**.

In **12d Model 14**, the default place for **User** is `c:\12d\14.00\User` but it could also be pointed to by the environment variable **USER\_4D**.

For **12d Model 15**, you need to create a new **User** folder and copy to it any files from the **12d Model 14 User** folder that you want to use with **12d Model 15**. You may need to copy the whole of the **12d Model 14 User** folder to the new area.

The default location for the **12d Model 14 User** folder is `c:\12d\14.00\User` but if the environment variable **USER\_4D** was used to point to a different location for the **User** folder in **12d Model 14** then you will probably want to use a non-standard **User** folder for **12d Model 15**. If that is the case then you will need to change **USER\_4D** in the *env.4d* file for **12d Model 15** to point to your **User** folder for **12d Model 15**.

### 3.6.2 Setting Up Your User\_Lib Folder for 12d Model 15

The folder **User\_Lib** contains your own library files and if you had files in a **User\_Lib** folder in **12d Model 14**, you will probably also want to use many of them with **12d Model 15**.

In **12d Model 14**, the default place for **User\_Lib** is `c:\12d\14.00\User_Lib` but it could also be pointed to by the environment variable **USER\_LIB\_4D**.

For **12d Model 15**, you need to create a new **User\_Lib** folder and copy to it any files from the **12d Model 14 User\_Lib** folder that you want to use with **12d Model 15**. You may need to copy the whole of the **12d Model 14 User\_Lib** folder to the new area.

The default location for the **12d Model 14 User\_Lib** folder is `c:\12d\14.00\User_Lib` but if the environment variable **USER\_LIB\_4D** was used to point to a different location for the **User\_Lib** folder in **12d Model 14** then you will probably want to use a non-standard **User\_Lib** folder for **12d Model 15**. If that is the case then you will need to change **USER\_LIB\_4D** in the *env.4d* file for **12d Model 15** to point to your **User\_Lib** folder for **12d Model 15**.

### 3.6.3 Setting Up Your env.4d File for 12d Model 15

The file *env.4d* contains environment variables that are used to customise **12d Model**.

An *env.4d* file is installed in the **Set\_Ups** folder when **12d Model** is installed and if a user wants to make any modifications to any of the environment variables in *env.4d*, then the modified *env.4d* file is placed in the **User** folder.

So if you have an *env.4d* file in your **User** folder in **12d Model 14**, you will probably also want to use it **12d Model 15**.

The default location for your modified *env.4d* file in **12d Model 14** is in your **User** folder for **12d Model 14** so for **12d Model 15**, you need to copy this *env.4d* file to your **User** folder in **12d Model 15**.

## 3.6.4 Are You Using a 12d Network Lock?

If you are using a **12d Network Lock** (**CodeMeter** or **Wibu**) for **12d Model 15**, then the file **dongles.4d** which is in the **User** folder contains the information to tell **12d Model** that it has to search for a network lock, and possibly which computer the network lock is on.

So if you are using a **12d Network Lock** for **12d Model 14**, you will need to copy your **12d Model 14 dongles.4d** file to the **12d Model 15 User** folder.

## 3.7 Network CodeMeters

### 3.7.1 Using a 12d Network CodeMeter for the First Time

If you are setting up **12d Model** to use a **12d Network CodeMeter** for the first time, please read the section [9 Network CodeMeters on page 55](#).

### 3.7.2 Updating Licenses in a Network CodeMeter

If you are modifying the virtual **12d Model** dongle within a Network CodeMeter (for example increasing the number of licenses), go to section [10.5 Updating Licenses in Network CodeMeters on page 112](#).

## 3.8 Documentation and What's New

The links for downloading documentation on **12d Model** are given in [6 Documentation on page 40](#).

The links for downloading documentation, power points and videos on what is new in **12d Model 15** are given in [7 What's New in 12d Model 15 on page 49](#).

This ends the Quick Installation notes for **12d Model 15**.

The rest of the Chapters in this document are:

[4 Detailed Notes for Installing 12d Model on page 12](#)

[5 Certifying CodeMeters on page 30](#)

[6 Documentation on page 40](#)

[7 What's New in 12d Model 15 on page 49](#)

[8 Errors Installing and Authorising on page 51](#)

[9 Network CodeMeters on page 55](#)

[10 CodeMeter Control Center & WebAdmin on page 80](#)

## 4 Detailed Notes for Installing 12d Model

These are the complete notes are for installing the **Release** version of **12d Model 15** using CodeMeter hardware locks. If you are using the older Wibu hardlock, please contact your Reseller for the installation notes.

**A. Disk Space required for installing **12d Model 15****

Approximately **3 Gigabytes** of disc space will be required for the installation to succeed.

**Before** installing **12d Model**, it is best to reboot the computer.

Your login must have **Administrator** privileges.

**B. Do not attach the 12d Model locks before installing dongle drivers**

The **12d CodeMeter** lock must **NOT be attached** to the computer before the CodeMeter drivers are installed during the **12d Model** installation.

**C. Installing**

The following **Steps** will take you through the combined installation **12d Model** and the CodeMeter drivers, and the setting up of the **nodes.4d** file.

Continue to [Step 1. Installing 12d Model 15 Release Version and CodeMeter Drivers on page 13.](#)

## Step 1. Installing 12d Model 15 Release Version and CodeMeter Drivers

The installer for **12d Model 15** is downloaded from the internet.

(a) Installing **12d Model** and CodeMeter Drivers from the Downloaded Files:


To download the installer for **12d Model**, click on

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12d\\_Model\\_15\\_C1f\\_64\\_Setup.exe](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12d_Model_15_C1f_64_Setup.exe)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.


Once the installer is downloaded, click on it (or run it) and the **12d Model** installation begins.

You may get a message warning you about not being able to verify who created the file:




Click on **Run** so that the installation can begin.

The **12d Model 15** installation starts by unpacking the information in the installation exe and then the installation begins.




If the Installer detects there is an existing version **12d Model 15** already installed, you will be asked if the Installer can **uninstall the existing version**. Unless this is done, the installation can not proceed.

**Note:** The uninstall deletes everything in the **Program Files\12d\12dmodel\15.00** folder so you should never modify any of those files.



Click on **Yes** to continue.

You then receive a **Warning** that the files will be deleted.




Click on **Yes** to continue.

All the files in the **Program Files \12d\12dmodel\15.00** folder will then be deleted, and the **12d Model xx** entry removed from the Windows Registry.

The installation of the new **12d Model** can now begin and the **Welcome** screen is displayed.

**Welcome**


*Welcome message*




Select **Next >** to continue with the installation

## Software License Agreement


12d Solutions license agreement



If you agree with the License conditions, tick on *I have read and accept the terms of the Software License Agreement*.



Select **Next >** to continue with the installation



**Tick on *12d Model* to install *12d Model*.**

**Tick on *CodeMeter Runtime* to install the latest CodeMeter drivers.**

**Tick on *12d Model Updater Service* to allow the installation of *12d Model* upgrades without being logged in as *Administrator*.**

**Tick on *Microsoft Visual C++ Redistributables* if this is the first time you have installed *12d Model 15*.**


Only tick on ***Courses and Training*** if you want to install the files for the ***Getting Started*** manuals. **NOTE:** These are currently only the ***V14*** training manuals

Only tick on ***Trimble Precision Runtime*** if you want to install the Trimble libraries.

Select ***Next >*** to continue with the installation



## Installation Location




Continue with the default installation folder for the software:

*C:\Program Files\12d\12dmodel\15.0*

or click on **Browse** to browse to another folder for the installation

Select **Next >** to continue with the installation

## User Area




Continue with the default folder for the **User Area** for the software:

*c:\12d\15.0*

or click on **Browse** to browse to another folder for the User Area.


Select **Next >** to continue with the installation

### Ready to Install




Click on **Install** to begin the actual installation

The software will be copied and installed onto the computer.




The Microsoft C++ Redistributables will be automatically installed



**DO NOT CLICK** on anything on the Microsoft Redistributable panels, especially **Cancel**. The panels will disappear by themselves.

### Setup Complete



End of the installation.

Select **Finish** to complete the installation

This completes the installation of the **12d Model** software and **CodeMeter** drivers.

If you have not used a CodeMeter hardware lock on the computer before, then the CodeMeter can now be attached to the computer. Go to [Step 2. Attach the Dongle on page 19.](#)

If you have already been using a CodeMeter hardware lock on the computer then go to [Step 3. SPECIAL NOTE ON CERTIFYING CODEMETERS on page 21.](#)

### Step 2. Attach the Dongle

The **12d Model** CodeMeter hardware lock can now be attached to the computer.

#### For USB dongles:


**Warning: you must have System Administration rights the first time you attach a USB dongle to any USB port:**

When a USB dongle is attached for the first time to any USB port, Windows will detect that it is new hardware and needs to load the dongle drivers for that USB port - this will require System Administration rights.

Since the dongle drivers have already been loaded onto your computer, when the USB dongle is attached to a new USB port, it will be recognised as new hardware



and Windows should automatically install the correct dongle driver.



**IMPORTANT NOTE IF THE CODEMETER IS NOT RECOGNISED:**

If the CodeMeter hardware lock is not recognised you get the **Found New Hardware** screen



please go to the section on how to find the Wibu drivers

**NOTE** - even though your CodeMeter is working on one USB port, if you try and attach the CodeMeter to a new USB port, the CodeMeter drivers will need to be installed for the new USB port. You will need System Administration rights to install the CodeMeter drivers on the **new** USB port.

For **12d Model** to run, the CodeMeter must be attached to the USB port at all times, otherwise **12d Model** will stop and ask you to save and exit.

### Step 3. SPECIAL NOTE ON CERTIFYING CODEMETERS

The **12d CodeMeters** must communicate over the Internet with a **Wibu Time Server** every two months to check that there is no problem with the **CodeMeter** that your **12d Model** license is using. This is called **Certifying** the **CodeMeter**.

For Certification to occur, a computer that can access the **CodeMeter** must also have access to the Internet to run the **Certification**.

One month before the end of the two month period, **12d Model** brings up the **Certify CodeMeter Dongle** panel which gives the number of days, minutes and seconds remaining until Certification is required.

If you are using a new CodeMeter from your **12d Model Reseller**, then it will usually come already Certified.

For more information on Certifying, see [5 Certifying CodeMeters on page 30](#).

**12d Model** will not function without an authorisation file called **nodes.4d**.

The final step is to install and test the **nodes** file. Go to [Step 4. Installing the Nodes.4d file on page 22](#).

#### Step 4. Installing the **Nodes.4d** file

**12d Model** will not create new projects or open existing projects without an authorisation file called **nodes.4d** with valid information in it.


The information inside **nodes.4d** controls

- (a) **which 12d dongles** are authorised to run **12d Model**
- (b) what **version** of **12d Model** will run for a dongle
- (c) what **modules** are authorised to run for a particular 12d dongle

To authorise **12d Model** to run with **your 12d dongles**, a file called **nodes.12dxxn** where **xx** is the **12d Model** version number, will have been emailed to you by your local **12d Model** Reseller.

For example, for **12d Model 15** the file will be called **nodes.12d15n**

Subject: 12D Auth file for 12D Solutions - Lee; Product 12d Model - 5c2d47013c -

Attachments:  nodes.12dXXn (11 KB)

Nodes file for : 12D Solutions - Lee  
- 5c2d47013c -

The authorization file for 12d Model - is attached to this message.

The self-install procedure which follows is for this one workstation and requires 12dmodel installed.  
After 12d Model version **XX** is installed, please double click on the file attachment [nodes.12dXXn] & to open it and 12d will guide you through.

If this succeeds you do not need to read further.


If this does not work it may be that the mail programme does not allow you to run attachments.  
In this case, simply save the attached file to your desktop and open (from the right-mouse menu or by double-click).  
This will start the installation for the nodes file.

Instructions for manual Installation:  
For version **XX** of 12d Model, usually goes in the folder  
"12d\XX.00" and once there it must be renamed to "nodes.4d"


Codemeter dongles require a driver installation which can be obtained here  
<http://www.wibu.com/en/downloads-user-software.html>  
If the product is still not authorized after replacing or updating "nodes.4d"  
please contact 12D Solutions on (61)(02) 9970 7117 or email support@12d.com

Installing **12d Model xx** on a computer sets up a *Windows* file association so that a **nodes.12dxxn** file is recognised and brings up the **Install a 12d Model xx Nodes File** panel which is used to install a **nodes.4d** file in the correct location.

In the email, double click on the files **nodes.12dxxn** and the **Opening Mail Attachment** panel comes up.



Click on **Open** and then the **Install a 12d Model xx Nodes File** panel appears



The choices for **Operation** are:

**Prepend** - if a **nodes.4d** file already exists, the information in the **nodes.12dXXn** file is added to the beginning of the existing **nodes.4d** file. A backup up copy of the existing **nodes.4d** is created.


**Replace** - if a **nodes.4d** file already exists, it is replaced by a new **nodes.4d** file with the information in the **nodes.12dxxn** file in the new **nodes.4d** file. A backup copy of the existing **nodes.4d** is created.

**Append** - if a **nodes.4d** file already exists, the information in the **nodes.12dxxn** file is added to the end of the existing **nodes.4d** file. A backup copy of the existing **nodes.4d** is created.

Select **Replace**, **Append** or **Prepend** and then click **Install**.

The new/updated **nodes.4d** file is created in the **Destination** folder (default is **C:\12d\lx.x.00**) and

if a **nodes.4d** file already existed, a backup copy of it is made.



**Note** - if you don't have the file **nodes.12dxxn** attached to an email but instead have the file in a folder accessible from your computer, then you can do the following:

If there is a **nodes.12dxxn** file, double click on that file and the **Install a 12d Model Nodes File** panel should appear and you continue as per the instructions above.

If that doesn't work, start up **12d Model xx** and click on the **Nodes.4d** button at the bottom of the **Open a Recent Project** panel. This will also bring up the **Install a 12d Model Nodes File** panel and you can browse for the **nodes.12dxxn** file in the **Source** panel field. You can then continue as per the instructions above.

**CONGRATULATIONS** - **12d Model** has now been successfully installed.

The folders and icons that are created in the installation are given in the sections:

[4.1 Folders Created by the Installation on page 26](#)

[4.2 Icons Created by the Installation on page 28,](#)

If **12d Model** did **not** install correctly and an **Authorization Error** panel came up, go to the section, [8 Errors Installing and Authorising on page 51](#), of these notes.

To obtain documentation for **12d Model**, go to [6 Documentation on page 40](#).

#### **Expanded Important Note on Nodes.12d15n and Nodes.4d**

The **12d Model 15 nodes.12d15n** file will normally be emailed to you.

During the installation of **12d Model 15**, an association is created for files ending in **.12d15n** so after the installation, opening the **nodes.12d15n** on the email will bring up the **Install a 12d Model Nodes File** program which can copy the information in the **nodes.12d15n** file to the required area (normally C:\12d\15.00) and **nodes.4d** file.

If you do not have the **nodes.12d15n** attached to an email but instead have it in a folder and have installed **12d Model 15**, double clicking on the **nodes.12d15n** file will also bring up the **Install a 12d Model Nodes File** program which can copy the information in the **nodes.12d15n** file to the required area (normally C:\12d\15.00) and **nodes.4d** file.

Or if the **12d Model 15** icon is clicked on, the **Open a Recent Project** panel comes up and clicking



on the **Nodes** button will also bring up the ***Install a 12d Model Nodes File*** program which can copy the information in the *nodes.12d15n* file to the required area (normally C:\12d\15.00) and ***nodes.4d*** file


Please **do not change** the **name** of the created ***nodes.4d*** file. **12d Model** will only search for an authorization file called *nodes.4d*.

# 4.1 Folders Created by the Installation

The **12d Model** installation loads the **12d Model software** into the folder

C:\Program Files\12d\12dmodel\15.00

**12d Model** users normally only have **read** access to the *Program Files* folders.




**12d Model software area under Program Files**

The **12d Model** installation also creates an area

C:\12d\15.00

which during the installation is given read/write access for the user.

If the **Courses and Training** component was ticked, then the installation will place the training data used with the *Getting Started for Design and Getting Started for Surveying* manual in the folder **12d\15.00** (or the folder you selected)



The folder **12d\15.00** is also the default folder where the *nodes.4d* file will be installed, and is also the default area where a user creates their own subfolders **User** and **User\_Lib** for their user configurations of **12d Model**.


### Warning

An Uninstall will **NOT** delete any of the training material loaded into **12d\15.0\training** and **12d\15.0\courses** by a previous installation.

The **12d Model 15** Install will overwrite any files of the same name in these areas.

## 4.2 Icons Created by the Installation

The installation loads the appropriate components and creates the **12d Model 15** icon



*icon for 12d Model 64 bit exe*

The **12d Model 15 - 64** icon fire up **12d Model** and attaches to the folder **12d\15.00**.

## 4.3 Copying Existing User, User\_Lib and env.4d

If you have **12d Model 14** installed on your computer, then you will probably want the files in the folders **User** and **User\_Lib**, and **env.4d** to be used for **12d Model 15**.

- (a) The folder **User** contains your files that are to replace those that **12d Model** installs in *Set\_ups* (e.g. *names.4d*, *linestyl.4d*) and if you already have some, you will probably also want to use them for **12d Model 15**.

For **12d Model 14**, the default place for **User** is `c:\12d\14.00\User` but it could also be pointed to by the environment variable `USER_4D`.

If there is an existing **User** folder, you need to create a new **User** folder for **12d Model 15** and copy to it any files that you want for **12d Model 15**.

The default place for the new **User** in **12d Model 15** is `c:\12d\15.00\User` but if `USER_4D` in your **V14 env.4d** was used to point to your **V14 User** then you will need to change `USER_4D` in your **V15 env.4d** to point to your **V15 User** folder

You may need to copy the whole of **User** to the new area.

- (b) The folder **User\_Lib** contains your own library files and you will probably also want to use them for **12d Model 15**.

For **12d Model 14**, the default place for **User\_Lib** is `c:\12d\14.00\User_lib` but it could also be pointed to by the environment variable `USER_LIB_4D`.

If there is an existing **User\_Lib** folder, you need to create a new **User\_Lib** folder for **12d Model 15** and copy to it any files that you want for **12d Model 15**.

The default place for the new **User\_Lib** in **12d Model 15** is `c:\12d\15.00\User_Lib` but if `USER_LIB_4D` in your **V14 env.4d** was used to point to your **V14 User\_Lib** then you will need to change `USER_LIB_4D` in your **V15 env.4d** to point to your **V15 User\_Lib** folder

You may need to copy the whole of **User\_Lib** to the new area.

- (c) Setting Up Your **env.4d** File for 12d Model 14

The file **env.4d** contains environment variables that are used to customise **12d Model**.

An **env.4d** file is installed in the *Set\_Ups* folder when **12d Model** is installed and if a user wants to make any modifications to any of the environment variables in **env.4d**, then the modified **env.4d** file is placed in the **User** folder.

So if you have an **env.4d** file in your **User** folder in **12d Model 14**, you will probably also

want to use it **12d Model 15**.

The default location for your modified **env.4d** file in **12d Model 14** is in your **User** folder for **12d Model 14** so for **12d Model 15**, you need to copy this **env.4d** file to your **User** folder in **12d Model 15**.

(d) Are you using a 12d Network Lock ?

If you are setting up **12d Model** to use a **12d Network CodeMeter** for the first time, please read the section [7 What's New in 12d Model 15 on page 49](#).

If you are using a **12d Network Lock (CodeMeter or Wibu)** for **12d Model 14**, then the file **dongles.4d** which is in the **User** folder contains the information to tell **12d Model** that it has to search for a network lock, and possibly which computer the network lock is on.

So if you are using a **12d Network Lock** for **12d Model 14**, you will need to copy your **12d Model 14 dongles.4d** file to the **12d Model 15 User** folder.

## 4.4 End of the Notes for Installing 12d Model 15

This ends the detailed notes for installing **12d Model 15**.

If you need to set up a **Network CodeMeter**, go to the section [9 Network CodeMeters on page 55](#).

The links for downloading documentation on **12d Model** are given in [6 Documentation on page 40](#).

The links for downloading information, power points and videos on what is new in **12d Model 15** are given in [7 What's New in 12d Model 15 on page 49](#).

The rest of the chapters in this document are

[6 Documentation on page 40](#)

[7 What's New in 12d Model 15 on page 49](#)

[8 Errors Installing and Authorising on page 51](#)

[9 Network CodeMeters on page 55](#)

[10 CodeMeter Control Center & WebAdmin on page 80](#)

## 5 Certifying CodeMeters

CodeMeters use the **Certified Time** capability of the CodeMeter and the CodeMeter must communicate **over the Internet** with a certified Time Server every two months to check that there is no problem with the CodeMeter, and to **update** the **Certified time** in the CodeMeter.


This process is called **Certifying the CodeMeter**.

Certifying a CodeMeter can be done

- (a) manually from inside **12d Model** itself  
Already documented. See [5.1 Certifying CodeMeters from 12d Model on page 30](#)
  - (b) automatically by **12d Model**  
Already documented. See [5.2 Automatically Certifying CodeMeters from 12d Model on page 32](#)
  - (c) outside of **12d Model** when the CodeMeter is on the computer you are using outside  
Using **CodeMeter Control Centre** - already documented in [5.3 Certifying CodeMeters Using Control Center on page 33](#).
- or
- (d) outside **12d Model** when the CodeMeter is **NOT** on the computer your are using  
It is possible to certify CodeMeters that are on other computers but this is usually only needed by Administrators. See [10.3.1 Certifying CodeMeters Using WebAdmin on page 90](#)

### 5.1 Certifying CodeMeters from 12d Model

One month before the end of the two month period, **12d Model** will bring up the **Certify CodeMeter Dongle** panel which gives the number of days, minutes and seconds remaining until Certification is required.



The **Certify CodeMeter Dongle** panel can also be brought up from within **12d Model** by the option  
**Project =>Management =>Dongles =>Certify CodeMeter**

The **Certified time** for that **CodeMeter** is updated to the current date by clicking on the **Certify** button.

### **Important Note**


There is an environment variable **AUTO\_CERTIFY\_DONGLE\_4D** and if it is set on then when the warning period is active for the CodeMeter (dongle) being used by **12d Model, 12d Model** will automatically attempt to certify the CodeMeter and if successful, no intervention by the user is required. See [5.2 Automatically Certifying CodeMeters from 12d Model on page 32](#).

## 5.2 Automatically Certifying CodeMeters from 12d Model

**12d Model** can automatically attempt to certify the CodeMeter whenever it is within the warning period (within one month of the two months after the Certified Time).

If the environment variable **AUTO\_CERTIFY\_DONGLE\_4D** to 1, whenever **12d Model** is started up, then if it is in the warning period **12d Model** will automatically attempt to certify the dongle. And if successful, no user intervention is required.

The environment variable **AUTO\_CERTIFY\_DONGLE\_4D** is set by the **Edit Environment Variables** panel. which is brought up by the **Projects =>Management =>env.4d** option.



Please contact your **12d Model Reseller** if you are having problems certifying your **CodeMeter**.

### Note

Any computer which has the environment variable **AUTO\_CERTIFY\_DONGLE\_4D** set to 1 can certify the **Network CodeMeter** that it is using to obtain a license from a **12d dongle**.

Please contact your **12d Model Reseller** if you are having problems certifying your **CodeMeter**.




## 5.3 Certifying CodeMeters Using Control Center


The Certified Time for any **CodeMeter** attached to your current computer can be displayed by using the **CodeMeter Control Center** which is brought up by clicking on the **CodeMeter** icon that was installed on your task bar.



The **CodeMeter Control Center** shows any **CodeMeters** that are attached to the this computer.



The Certified Time in a CodeMeter that is on this computer can be displayed and updated by clicking on **Process >Update Time Certificates**



**Note**

If the **CodeMeter** is not on the computer you are using the then certifying the codemeter must be done using **CodeMeter WebAdmin** (see [10.3.1 Certifying CodeMeters Using WebAdmin on page 90](#)).

## 5.4 Installing the CodeMeter Drivers Separately

For some reason you may want to install the CodeMeter drivers separately to the **12d Model** installation. In that case you only need to download the CodeMeterRuntime\_7\_30a.exe which is downloaded from:

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/CodeMeterRuntime\\_7\\_30a.exe](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/CodeMeterRuntime_7_30a.exe)

**WARNING** You need to have System Administrator rights to install the CodeMeter drivers

Once you have downloaded **CodeMeterRuntime\_7\_30a.exe**, click on it to begin the installation process.

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Installing the CodeMeter Drivers:

The script to install the **CodeMeter** drivers begins.

**CodeMeter Setup**


*CodeMeter Runtime Kit Setup*



Select **Next** to continue.

## End-User License Agreement


## CodeMeter Runtime Kit Setup



Read the License Agreement and if you are happy with it, tick "I accept the terms in the License Agreement" and then select **Next** to continue.

## Installation Scope

## CodeMeter Runtime Kit Setup




Enter your **User name** and **Organisation**.

Click on either **Install just for you** or **Install for all users of this machine** and then select **Next** to continue.

## Custom Setup


## CodeMeter Runtime Kit Setup



Select **Next** to continue.

## Ready to Install


## CodeMeter Runtime Kit Setup



Select **Install** to continue.


**Installing**

*CodeMeter Runtime Kit Setup*



**Completed**

*CodeMeter Runtime Kit Setup*



Select **Finish** to end.

**Note:** A **CodeMeter** icon, that is used to bring up the **CodeMeter Control Center**, is also installed on your task bar.



**Important Notes**

1. Do not attach a hardware lock to your computer until after the appropriate driver is installed

2. The CodeMeter drivers need to be at least version **6.3**.

If your computer already has drivers installed and they are NOT at least version **6.3**, when **12d Model 15** starts it will stop and complain that the hardware lock drives are **NOT** up to date.

If that is the case then

- (a) Uninstall the existing CodeMeter drivers
- (b) Install new CodeMeter drivers. See [5.4 Installing the CodeMeter Drivers Separately](#).

If you were installing the CodeMeter drivers as part of setting up a **Network CodeMeter**, go to [What is Done to the Computer By Step 1](#).

After CodeMeter drivers have been installed, the CodeMeter can be attached to the computer. Go to [Step 2. Attach the Dongle](#).

# 6 Documentation

See

- [6.1 12d Model Reference Manual on page 40](#)
- [6.2 Getting Started for Design Manual on page 42](#)
- [6.3 Getting Started for Surveying Manual on page 44](#)
- [6.4 12d Model Programming Language Manual on page 46](#)
- [6.6 12dxml File Format on page 47](#)
- [6.7 12da File Format on page 48](#)
- [7 What's New in 12d Model 15 on page 49](#)

## 6.1 12d Model Reference Manual

The **12d Model Reference** manual contains the technical information required for using **12d Model** includes information such as:

- (a) the tools and concept used in **12d Model**
- (b) descriptions of the **12d Model** screen layout, views and toolbars
- (c) information on each **12d Model** menu
- (d) technical information on the fields in each **12d Model** panel
- (e) information on all the set up files for **12d Model**. For example, for colours and linestyles
- (f) information on the **12d XML** and **12da** file formats
- (g) information on the **12dfield** and **fid** file formats

Although the **12d Model Reference** manual contains some information on each of the field in panels, it is the technical information about what is valid values etc and is not intended to be a full description on how all the options work together. That is, it is **NOT a training manual**.


The **12d Model Reference** manual also acts as a **context sensitive Help** system when **12d Model** is running.

That is, when **12d Model** is running:


- (a) for most menus in **12d Model**, when the menu is on the screen and has the Windows focus, pressing F1 will open the **12d Model Reference** manual at that menu
- (b) for most panels in **12d Model**, when the panel is on the screen and has the Windows focus, pressing F1 will open the **12d Model Reference** manual at that panel. Or if the panel has a **Help** button, clicking on the **Help** button opens the **12d Model Reference** manual at that panel.

The full **12d Model Reference** manual is can be accessed from within **12d Model** by clicking on the option **Help =>12d Model**.





The **12d Model Reference** is a pdf file and when **12d Model** is installed, it is copied into the **Help** folder.



To download a zipped copy of the **12d Model Reference** manual, **12d.pdf**, click on the following link and then unzip the downloaded file

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12d\\_ref\\_V15\\_C1f.zip](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12d_ref_V15_C1f.zip)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Continue to [6.2 Getting Started for Design Manual](#) or return to [6 Documentation](#).

## 6.2 Getting Started for Design Manual

### WARNING

At the moment this is only the **Getting Started for Design** manual for **12d Model 14**


The **Getting Started** manuals are currently being rewritten using a different data set.

**12d Model** is supplied with a comprehensive on-line **12d Model Reference** manual which describes the function of each menu option in detail. However, it is a **Reference** manual and makes no attempt to describe how to use **12d Model** for production surveying and civil engineering work.


The **12d Model Getting Started for Design** manual is designed to show you how to work with the context sensitive help system, and then as the first section of Training, help you start to learn how to use **12d Model** to achieve typical civil engineering tasks.

Wherever possible, The **12d Model Getting Started for Design** manual uses examples to clarify usage. It compliments rather than replaces the **12d Model Reference** manual. In general, information in the **12d Model Reference** manual will not be duplicated in the **12d Model Getting Started for Design** manual.

The **12d Model Getting Started for Design** manual can be accessed from within **12d Model** by clicking on the option **Help =>Getting Started for Design**



The **12d Model Getting Started for Design** manual is a pdf file and when **12d Model** is installed, it is copied into the **Help** folder.



To download a pdf copy of the **12d Model Getting Started for Design** manual, click on the

following link

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12dm\\_getting\\_started\\_for\\_design\\_V14.pdf](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12dm_getting_started_for_design_V14.pdf)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Continue to [6.3 Getting Started for Surveying Manual](#) or return to [6 Documentation](#).

## 6.3 Getting Started for Surveying Manual

### WARNING

At the moment this is only the **Getting Started for Surveying** manual for **12d Model 14**.


The **Getting Started** manuals are currently being rewritten using a different data set.

**12d Model** is supplied with a comprehensive on-line **12d Model Reference** manual which describes the function of each menu option in detail. However, it is a **Reference** manual and makes no attempt to describe how to use **12d Model** for production surveying and civil engineering work.


The **12d Model Getting Started for Surveying** manual is designed to show you how to work with the context sensitive help system, and then as the first section of Training, help you start to learn how to use **12d Model** to achieve typical surveying tasks.

Wherever possible, The **12d Model Getting Started for Surveying** manual uses examples to clarify usage. It compliments rather than replaces the **12d Model Reference** manual. In general, information in the **12d Model Reference** manual will not be duplicated in the **12d Model Getting Started for Surveying** manual.

The **12d Model Getting Started for Surveying** manual can be accessed from within **12d Model** by clicking on the option **Help =>Getting Started for Surveying**



The **12d Model Getting Started for Surveying** manual is a pdf file and when **12d Model** is installed, it is copied into the **Help** folder.



To download a pdf copy of the **12d Model Getting Started for Surveying** manual, click on the following link

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12dm\\_getting\\_started\\_for\\_surveying\\_V14.pdf](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12dm_getting_started_for_surveying_V14.pdf)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Continue to [6.4 12d Model Programming Language Manual](#) or return to [6 Documentation](#).


## 6.4 12d Model Programming Language Manual

The **12d Model Programming Language** (12dPL), is a powerful programming language designed to run from within **12d Model**. It is also known as 4DML from when the product was called **4d Model**.


Its main purpose is to allow users to enhance the existing **12d Model** package by writing their own programs. These programs are often called **macros**.

The **12d Model Programming Language** manual is a reference manual and does not try to teach programming techniques. Instead this manual sets out the syntax, restrictions and supplied functions available in 12dPL.

The **12d Model Programming Language** manual can be accessed from within **12d Model** by clicking on the option **Help =>12d Macro Manual**



The **12d Model Programming Language** manual is a pdf file and when **12d Model** is installed, it is copied into the **Help** folder.



To download a pdf copy of the **12d Model Programming Language** manual, 12d\_prog.pdf, click on the following link

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12d\\_prog\\_V15\\_C1f.pdf](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12d_prog_V15_C1f.pdf)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Continue to [6.5 12d Field File Format](#) or return to [6 Documentation](#).

## 6.5 12d Field File Format

The **12d Field File Format** manual contains the documentation of the **12d Model** raw survey file format **.12dfield**, and the older raw survey file format, **.fld**.

The **12d Field File Format** is part of the **12d Model Reference** manual (see [6.1 12d Model Reference Manual](#)) but the chapter as also been separated out so the entire **12d Model Reference** manual is not needed.

To download a pdf copy of the **12d Field File Format** manual, click on the following link

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12d\\_Field\\_File\\_Format\\_V15\\_C1f.pdf](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12d_Field_File_Format_V15_C1f.pdf)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Continue to [6.6 12dxml File Format](#) or return to [6 Documentation](#).

## 6.6 12dxml File Format

The **12dxml** file format is a text file definition from **12d Solutions** which is used for reading and writing out string data from **12d Model**. **12dxml** files normally end in **.12dxml**.

The **12dxml** file is a Unicode file.

The documentation for **12dxml** is part of the **12d Model Reference** manual (see [6.1 12d Model Reference Manual](#)) but the chapter as also been separated out so the entire **12d Model Reference** manual is not needed.

To download a pdf copy of the **12d Model 12dxml** manual, click on the following link

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12d\\_xml\\_File\\_Format\\_V15\\_C1f.pdf](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12d_xml_File_Format_V15_C1f.pdf)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Continue to [6.7 12da File Format](#) or return to [6 Documentation](#).

## 6.7 12da File Format

The **12da** (12d Archive) file format is a text file definition from **12d Solutions** which is used for reading and writing out string data from **12d Model**. **12da** files normally end in **.12da**.

The **12da** file is a Unicode file.

The documentation for **12da** is part of the **12d Model Reference** manual (see [6.1 12d Model Reference Manual](#)) but the chapter has also been separated out so the entire **12d Model Reference** manual is not needed.

To download a pdf copy of the **12da File Format** manual, click on the following link

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/12d\\_A\\_File\\_Format\\_V15\\_C1f.pdf](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/12d_A_File_Format_V15_C1f.pdf)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

### Further Notes:

1. **12da** was originally an Ascii file and stood for **12d Ascii** but now that the **12da** file is a Unicode file, **12da** stands for **12d Archive**.
2. 12da has now been superseded by 12d xml (see [6.6 12dxml File Format](#))

Continue to [7 What's New in 12d Model 15](#) or return to [6 Documentation](#).



# 7 What's New in 12d Model 15

This chapter contains links to information on many of the new things in **12d Model 15**.

See

[7.1 What's New pdf on page 49](#)

[7.2 What's New Summary of Additions Sorted by Sub-Version on page 49](#)

[7.3 What's New Summary of Fixed Bugs Sorted by Sub-Version on page 49](#)

[7.4 What's New Summary of All Additions up to V15C1f on page 50](#)

[7.5 What's New Summary of All Fixed Bugs up to V15 C1f on page 50](#)

## 7.1 What's New pdf

The **What's New in 12d Model 15 pdf** gives detailed information on many of the new options and features in **12d Model 15**.

[https://downloads.12dmodel.com/V15/12d\\_Model\\_15\\_C1f/Whats\\_New\\_in\\_12d\\_Model\\_15\\_C1f.pdf](https://downloads.12dmodel.com/V15/12d_Model_15_C1f/Whats_New_in_12d_Model_15_C1f.pdf)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

## 7.2 What's New Summary of Additions Sorted by Sub-Version

A one line summary of all the additions in **12d Model 15**, broken into **sub-versions** (i.e. C1f downwards) and subsorted by **Components**:

[https://downloads.12dmodel.com/V15/12d\\_Model\\_15\\_C1f/WNS\\_V15\\_new\\_to\\_C1f\\_split.htm](https://downloads.12dmodel.com/V15/12d_Model_15_C1f/WNS_V15_new_to_C1f_split.htm)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

## 7.3 What's New Summary of Fixed Bugs Sorted by Sub-Version

A one line summary of all the bugs fixed in **12d Model 15**, broken into **sub-versions** (i.e. C1f downwards) and subsorted by **Components**:

[https://downloads.12dmodel.com/V15/12d\\_Model\\_15\\_C1f/WNS\\_V15\\_bugs\\_fixed\\_to\\_C1f\\_split.htm](https://downloads.12dmodel.com/V15/12d_Model_15_C1f/WNS_V15_bugs_fixed_to_C1f_split.htm)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

## 7.4 What's New Summary of All Additions up to V15C1f

A one line summary of all the additions in **12d Model 15**, sorted by **Component**:

[https://downloads.12dmodel.com/V15/12d\\_Model\\_15\\_C1f/WNS\\_V15\\_new\\_to\\_C1f.htm](https://downloads.12dmodel.com/V15/12d_Model_15_C1f/WNS_V15_new_to_C1f.htm)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

## 7.5 What's New Summary of All Fixed Bugs up to V15 C1f

A one line summary of all the bugs fixed in **12d Model 15**, sorted by **Component**:

[https://downloads.12dmodel.com/V15/12d\\_Model\\_15\\_C1f/WNS\\_V15\\_bugs\\_fixed\\_to\\_C1f.htm](https://downloads.12dmodel.com/V15/12d_Model_15_C1f/WNS_V15_bugs_fixed_to_C1f.htm)

**Note:** If clicking on the link does not start up your Browser then copy the text of the link into your Browser.

Return to [7 What's New in 12d Model 15](#).

# 8 Errors Installing and Authorising

See

[8.1 12d Model XX Not Authorising on page 51](#)


[8.2 Licence Expiry Warning on page 52](#)

[8.3 Dongle Missing on page 53](#)

## 8.1 12d Model XX Not Authorising

If there is an **error** with the installation, then the **Error Authorizing Release Version** panel appears with the error messages in the panel message area.

For example, for **12d Model 11**




In the above panel, the UNKNOWN in the **Dongle number** column shows that no **12d** dongle has been detected.

If there is no error message on the panel or it is still not obvious what the problem is, please contact your **12d Model Reseller**.

## 8.2 Licence Expiry Warning

The **nodes.4d** file that controls **12d Model**, only validates **12d Model** to run for a certain period of time.

If when running **12d Model**, the **Licence Expiry Warning** panel appears:




it simply means that the **nodes.4d** file needs to be updated.

Please contact your **12d Model Reseller** to obtain a new **nodes file** before the given date. If this is not done then **12d Model** will no longer run until you do obtain and install a new nodes file.

## 8.3 Dongle Missing

If when running **12d Model**, the **Dongle Missing** panel appears:



it simply means that the **12d** dongle can no longer be seen by **12d Model**.

Please check that your **12d** dongle is still attached to your computer, or if you are using a network dongle, that your network is still active.

Then click on **Retry**, and if that doesn't work, click on **Dongle retry**.

Even if you still can not see the dongle, **12d Model** will allow you to save your current work so that nothing is lost by clicking on the **Save and exit 12d** button.



# 9 Network CodeMeters

A **12d Local CodeMeter** (also known as a **Standalone** or **single-user CodeMeter**) is a CodeMeter that is attached to a computer that only allows **12d Model** to be run on **that computer**.

If the **12d Local CodeMeter** is to be used on another computer then the **12d Local CodeMeter** must be moved to the other computer. This means that **12d Model** will no longer run on the computer without the **12d Local CodeMeter**.





This is the default installation for **12d Model**.

A **12d Network CodeMeter** is a CodeMeter that controls a number of **12d Model** licenses and the **12d Network CodeMeter** can potentially be accessed by **any other computer on the network**, and allows copies of **12d Model** to be run on those computers without needing a **12d Local CodeMeter**.

The **12d Model** licenses controlled by the **12d Network CodeMeter** can be accessed and used in any country and any time zone, subject to any Australian and local Laws that may prevent it.

The only restriction is that each instance of **12d Model** on a computer requires its own **12d Model** license from the **12d Network CodeMeter**.

**12d Network CodeMeters** are metallic and a silver colour, and are labelled with a number starting with **ec**.

<b>12d Local CodeMeter also referred to as a Single User or Standalone CodeMeter</b>		<b>12d Network CodeMeter</b>	
<b>Stubby USB</b>		<b>Long USB</b>	<b>Silver USB</b>
with end cap and ring	without end cap and ring		
			
<b>Note:</b> the end cap and ring are cosmetic only			

**Note:** When using a **12d Network CodeMeter**, each running copy of **12d Model** using a **12d Network CodeMeter** on a computer requires a license from the **12d Network CodeMeter**.

If your computer is not using a **12d Local CodeMeter** and is only using a **12d Network CodeMeter** to obtain **12d Model** licenses then **12d Model** and the CodeMeter Drivers **still need to be installed on the computer** that is wanting to run **12d Model**.

**BUT** when **12d Model** is installed it is set up for users with a **Local (single user or stand alone)** CodeMeter and installs a **dongles.4d** file that assumes that **12d Model** is only using a **12d Local CodeMeter** and has no access to a **12d Network CodeMeter**.

So to access a **12d Network CodeMeter**, the **dongles.4d** file needs to be modified and the **nodes.4d** file you use will need to contain an authorization for the **12d Local CodeMeter**.

**Note:** a computer can be set up to look for both a **12d Local CodeMeter** and a **12d Network CodeMeter**.

To install the **Network CodeMeter** and configure computers to use the Network CodeMeter, you will need

## 1. First Install the CodeMeter drivers

### IMPORTANT WARNING

Do not attach any CodeMeters, Network or Standalone, to your computer until after you have installed the CodeMeter Drivers.

The latest CodeMeter Drivers installation program **12d\_dongles\_installation\_date.exe** is downloaded from:

[https://downloads.12dmodel.com/v15/12d\\_Model\\_15\\_C1f/CodeMeterRuntime\\_7\\_30a.exe](https://downloads.12dmodel.com/v15/12d_Model_15_C1f/CodeMeterRuntime_7_30a.exe)

For the notes for installing the CodeMeter Drivers separately, see [5.4 Installing the CodeMeter Drivers Separately on page 35](#).

2. a **nodes.4d** file to authorize the **12d Model xx** licenses controlled by the **12d Network CodeMeter** where **xx** is the **12d Model** versions required.

This is usually supplied in an email a the attached file **nodes.12dxxn** (for example, for **12d Model 15**, it will be **nodes.12d15n**)

Or you may already have it in a folder with the **12d Model** authorization file **nodes.12dxxn** or **nodes.4d** in it.

Full instructions setting up Network CodeMeters, and making the required modifications to the **dongles.4d** file and the **nodes.4d** file, are given in the rest of this chapter.


Continue to [9.1 Definitions and Guide to the Network Notes on page 57](#).



## 9.1 Definitions and Guide to the Network Notes

A **12d CodeMeter Server** is a computer with a **12d Network CodeMeter** attached to it. Note that this can be any computer, it does not have to be a Server Computer.

A **12d CodeMeter Client** is a computer that gets its **12d Model** licenses from a **12d CodeMeter Server**. The CodeMeter Client computer does not have a 12d Network CodeMeter attached to it.



Both **CodeMeter Servers** and **CodeMeter Clients** must have the **CodeMeter Drivers** and **CodeMeter Runtime Server** service installed and running and this is described in [9.2 Installing CodeMeter Drivers on page 59](#).

**CodeMeter Servers** must also have the **CodeMeter Network Server** running and this is described in [Step 6. Starting the 12d Network Server on page 67](#).

To run **12d Model** on a CodeMeter Client, an appropriate **dongles.4d** and valid **nodes.4d** file must be obtained and set up. This is describing in [9.4 dongles.4d and nodes.4d on page 69](#).

These notes are for

- (a) Installing and setting up a new 12d Network CodeMeter to act as a 12d License server
  - (b) Setting up other computers (Clients) so they can access the Network CodeMeter and **12d Model** licenses in the 12d Network CodeMeter.
  - (c) Setting up/Updating **dongles.4d** to instruct the other computers (Clients) which Network CodeMeters to use. This can be down to the level of using a **particular** virtual **12d dongle** inside a **particular** 12d Network CodeMeter.
  - (d) Setting up/Updating the **nodes.4d** file with the authorization to match the **12d dongle** being accessed inside a 12d Network CodeMeter.
  - (e) Updating the **12d Model** licenses in a 12d Network CodeMeter
- and
- (f) Monitoring 12d Network CodeMeters.

### WARNING

If the computers accessing a **12d Network CodeMeter** are in a **different subnet** (behind a

router) to the **12d Network CodeMeter** then **12d Model** needs to be given the IP address or the computer names of the servers with the **12d Network CodeMeter**. This will be explained later in the notes. This will also apply to computers connected by Wireless or DHCP.

If you already have a **12d Network CodeMeter** and are simply updating a **12d dongle** inside the **Network CodeMeter**, go to the section [10.5 Updating Licenses in Network CodeMeters on page 112](#).

If you are installing a **12d Network CodeMeter** on the computer for the first time, please continue to the next section [9.1 Definitions and Guide to the Network Notes on page 57](#).

### **Important Note for Going From 12d Local CodeMeters to 12d CodeMeter Servers**

The *CodeMeter drivers* are exactly the same ones that are used for a 12d Local (standalone or single-user) CodeMeter. So if a computer is already been used for a 12d Local CodeMeter with **12d Model**, then the *CodeMeter drivers* have already been installed and will not need to be installed again.

This means that if a **12d Network CodeMeter** is introduced, all the computers that are currently running **12d Model** with a Local CodeMeter will not need the CodeMeter drivers installed.

However, such **CodeMeter Client** computers will need a modification to their **dongles.4d** file to tell the computer that **12d Model** licenses can be obtained from a **12d Network CodeMeter** rather than just a 12d Local CodeMeter (see [9.4 dongles.4d and nodes.4d on page 69](#)).

Also a valid **nodes.4d** file for the **12d dongle** inside the **12d Network CodeMeter** is needed (see [10.5 Updating Licenses in Network CodeMeters on page 112](#)).

## 9.2 Installing CodeMeter Drivers

**IMPORTANT WARNING** - Do not attach a 12d CodeMeter to your computer until after you have installed the CodeMeter drivers.

This section is installing the CodeMeter drivers.

This must be done on the computer that will have the 12d Network CodeMeter attached to it (the **CodeMeter Server**) and also for all the computers that are **12d CodeMeter Clients** using the CodeMeter Server.

If the computer has **no** CodeMeter Drivers, or **old** CodeMeter Drivers, installed on it, go to [5.4 Installing the CodeMeter Drivers Separately on page 35](#).

If a computer is to become a CodeMeter Server but already has the CodeMeter Drivers installed on it, then go straight to [9.3 Setting up a 12d Network CodeMeter on page 62](#).

If the computer is already set up as a CodeMeter Server and you are adding a new **12d dongle** to the 12d Network CodeMeter, or upgrading the number of 12d licenses on a **12d dongle** in the 12d Network CodeMeter, go to [10.5.1.1 Updating Using the .WibuCmRaU File on page 116](#).

If you are replacing the existing 12d Network CodeMeter by a new 12d Network CodeMeter, go to [10.6 Replacing an Existing Network CodeMeter on page 120](#).


# What is Done to the Computer By Step 1

## 1. CodeMeter Drivers

The CodeMeter drivers that allows software to access CodeMeters anywhere on the network is installed.

## 2. CodeMeter Runtime Server

The service **CodeMeter Runtime Server** service is also installed and started on the computer and if you look in the **Services** tab of the *Windows Task Manager*, the **CodeMeter Runtime Server** will be shown as **Running**.



The screenshot shows the Windows Task Manager window with the 'Services' tab selected. A table lists several services, with 'CodeMeter.exe' highlighted by a red circle. The table has columns for Name, PID, Description, Status, and Group.

Name	PID	Description	Status	Group
dr_optimization_v4.0.30319_64		Microsoft .NET Framework NGEN v...	Stopped	N/A
CodeMeter.exe	12464	CodeMeter Runtime Server	Running	N/A
COMSysApp		COM+ System Application	Stopped	N/A


If for some reason the **CodeMeter Runtime Server** is shown as **Stopped**, to restart it again go to [Step 6. Starting the 12d Network Server on page 67.](#)

## 3. CodeMeter Icon

As well as installing the CodeMeter drivers., a **CodeMeter** icon is installed on your task bar



Clicking on the **CodeMeter** icon brings up the **CodeMeter Control Center** which shows any CodeMeters that are attached to the this computer. The **CodeMeter Control Center** also has options to stop and start the **CodeMeter Runtime Server** and bring up the **WebAdmin** panel to examine the content of CodeMeters anywhere on the network.



If the computer is to be a **CodeMeter Server**, then the next step is to check the Network CodeMeter. If this is the case then go to [9.3 Setting up a 12d Network CodeMeter on page 62](#).

If the computer is a **CodeMeter Client**, then the next steps are to

- (a) set up the **dongles.4d** file to see the **12d Network CodeMeter** (and if required a particular 12d dongle inside the 12d Network CodeMeter)

and

- (b) set up the **nodes.4d** with the authorization for the required 12d dongle number.

For setting up **dongles.4d** and **nodes.4d**, see [9.4 dongles.4d and nodes.4d on page 69](#).

## 9.3 Setting up a 12d Network CodeMeter

The **CodeMeter drivers** are now installed and the **CodeMeter Runtime Server** is running.

The next steps are to actually attach the 12d Network CodeMeter, examine its contents to make sure everything that are correct, and then start up the **12d Network Server** so that other computers in the network will be able to see and use the 12d Network CodeMeter.


These steps will complete the setting up of the 12d Network CodeMeter as a **12d CodeMeter Server**.

### Step 2. Attaching the Network CodeMeter

The **physical CodeMeter number** can be found on the part of the 12d Network CodeMeter that is pushed into the USB port (the CodeMeter shaft). The number starts with **2-**.

This number needs to be recorded but you need to have very good eyes to be able to read it or have a magnifying glass.


If the CodeMeter number can't be read, it is also possible to obtain the number after the 12d Network CodeMeter is plugged into the USB port of the computer (see [Step 3. Checking that the 12d Network CodeMeter is Visible on page 63.](#))



Now that the CodeMeter drivers are installed on the computer, the **12d Network CodeMeter** can now be attached to the USB port on the computer.

### Step 3. Checking that the 12d Network CodeMeter is Visible


Click on the **CodeMeter** icon that was installed on your task bar to bring up the **CodeMeter Control Center** which shows what CodeMeters are on this computer.



The CodeMeter number, that is written on the shaft of the CodeMeter, should be displayed in the **CodeMeter Control Center**.

### Step 4. What to Do If You Can't See the CodeMeter

If you were unable to see the CodeMeter number in the **CodeMeter Control Center** then first check that the service **CodeMeter Runtime Server** service is installed and running on the computer by looking in the *Windows Task Manager* and checking that **CodeMeter Runtime Server** is shown as **Running**.



If for some reason the **CodeMeter Runtime Server** is there but shown as **Stopped**, to restart it again see [Step 6. Starting the 12d Network Server on page 67.](#)

If you are still having problems then contact your **12d Model Reseller**.

### Step 5. Checking the Virtual 12d Virtual Dongles Inside the Network CodeMeter

The **12d Network CodeMeter** alone is not enough to provide a license to run **12d Model**.

There must also be a **12d virtual dongle** *inside* the Network CodeMeter.

It is the **12d virtual dongle** that controls how many network licenses of **12d Model** are available.

**Aside:**

The **12d virtual dongle** issues the **12d Model** licenses but the actual **12d Model** modules that go with a license from a **12d virtual dongle** is controlled by a matching entry in the **nodes.4d** file. This means that what **12d Model** modules you have can be updated by just adding a new entry for the nodes.4d file. The word **virtual** is used because the 12d virtual dongle is **NOT** a physical lock. The **12d virtual dongle** is often abbreviated to **12d dongle**.

Clicking on the **WebAdmin** button on the **CodeMeter Control Center** brings up the **CodeMeter WebAdmin** panel which is used to display information about any of the CodeMeters that it can see. **Note** - you may have one of two versions of WebAdmin - see [10.8 Which Version of WebAdmin? on page 121](#).

**For WebAdmin 6:**

Clicking on the tab **Content >Licenses** of the **CodeMeter WebAdmin** panel displays the **12d virtual dongle** information stored in the selected CodeMeter.

The screenshot shows the CodeMeter WebAdmin interface for a container named '<no name>' (ID: 2-2310233). The 'Licenses' tab is active, displaying a table of licenses. The table has columns for Product Code, Name, Unit Counter, Valid Until, License Quantity, and Feature Map. Two license entries are shown under product code 101956 (12d.com):

Product Code	Name	Unit Counter	Valid Until	License Quantity	Feature Map
1	12d Model - Stock - 12d Solutions - ec51470113	n/a	n/a	5	n/a
1	12d Model - Stock - 12d Solutions - ec51470114	n/a	n/a	25	n/a

Annotations below the table:

- 12d Product name: points to '12d Model - Stock - 12d Solutions - ec51470113'
- 12d Customer name: points to 'Stock - 12d Solutions'
- 12d virtual dongle number: points to 'ec51470114'
- Total number of licenses on the 12d virtual dongle: points to '25'

For instructions on how to select and see CodeMeters on a particular 12d Network Server, see [10.4.1 Getting Info on CodeMeters on a Particular Server - WebAdmin 6 on page 99](#)

**For WebAdmin 5:**

Clicking on the tab **Content >Licenses** of the **CodeMeter WebAdmin** panel displays the **12d virtual dongle** information stored in the selected CodeMeter.



CodeMeter WebAdmin

Home Content Server Configuration Diagnosis Info Help

CmContainer | Licenses | User Data | Backup/Restore

CmContainer: 2-2310262

100003   Bundling Articles					
Product Code	Name	Unit Counter	Expiration Time	Activation Time	License Quantity
1	SecuriKey Lite	n/a	n/a	n/a	1

101956   12d.com					
Product Code	Name	Unit Counter	Expiration Time	Activation Time	License Quantity
1	12d Model - 12d Solutions - ec51470022	n/a	n/a	n/a	3

12d Product name

12d virtual dongle number

12d Customer name

Total number of licenses on the 12d dongle

For instructions on how to select and see CodeMeters on a particular Network Server, see [10.4.3 Getting Info on CodeMeters on a Particular Server - WebAdmin 5 on page 106](#)


If there are no **12d dongle numbers** displayed inside the 12d Network CodeMeter, or no **12d dongle number** starting with **ec**, contact your **12d Model Reseller**.

You need to make a note of the **12d dongle number** because there must be a valid entry with the matching **12d dongle number** in the **nodes.4d** file.

**Note:** The **WebAdmin** button is only selectable if the **CodeMeter Runtime Server** is running. If it is **Stopped**, to restart it again see [Step 6. Starting the 12d Network Server on page 67](#).

### Important Note:

There may be **more than one 12d dongle number** inside the one physical CodeMeter Container. That is why they are also referred to as **virtual** 12d dongles. For example,



Within **12d Model**, it is possible to address specific 12d Network CodeMeters, and specific 12d dongles *within* a 12d Network CodeMeter. This is done via the **dongles.4d** file and how it is set up is described in [9.4.1 Updating dongles.4d on page 69](#).

## Step 6. Starting the 12d Network Server

For a **12d Network CodeMeter** to be seen and used by other computers in the network, the **12d Network Server** needs to be running **on the computer with the 12d Network CodeMeter** on it.

The **CodeMeter WebAdmin** panel is used to start the **12d Network Server**.

**Note:** The **12d Network Server** is controlled by the **CodeMeter Runtime Server** service so it is critical that the **CodeMeter Runtime Server** service is running.

To bring up the **CodeMeter WebAdmin** panel, click on the **WebAdmin** button on the **CodeMeter Control Center**.

### For WebAdmin 6:


In the **CodeMeter WebAdmin** panel, click on the **Configuration >Server >Server access** menu.

The screenshot shows the CodeMeter WebAdmin interface in a browser window. The URL is localhost:22350/configuration/server\_access.html. The navigation menu includes Dashboard, Container, License Monitoring, Diagnosis, Configuration, and Info. The Configuration menu is expanded, showing Basic, Server, and Advanced options. The Server option is selected, and the Server Access sub-menu is open. The Network Server section has the 'Enable' radio button selected, and the Network Port is set to 22350. The CmWAN Server section has the 'Enable' radio button selected, and the CmWAN Port is set to 22351. The 'Apply' button is highlighted with a red circle. A note at the bottom states: (\*) Changes only take effect after restarting CodeMeter.

Click on **Enable** and then **Apply**.

**For WebAdmin 5:**

In the **CodeMeter WebAdmin** panel, click on the **Configuration >Server** tab and then tick on **Run Network Server**.



Click on **Apply** and a message **Operation completed successfully - please wait** will appear and when it disappears, the above panel is displayed again.

The **12d Network Server** should now be running.

Note that unlike the **CodeMeter Runtime Server** service, the **12d Network Server** is not a service and so will not appear in the **Windows Task Manager**.

The computer with the 12d Network CodeMeter is now ready to use as a **12d CodeMeter Server**.

## 9.4 dongles.4d and nodes.4d

For **12d Model** to be able to create and/or open existing projects, it requires

- (a) a license from a **12d dongle** inside a **12d Network CodeMeter**
- and
- (b) a valid entry with the **matching 12d dongle number** in the **nodes.4d** file

Once **dongles.4d** and **nodes.4d** have been updated, they must be the **nodes.4d** and **dongles.4d** files that are used for any computer wanting to use a **12d Model** license from the **12d Network CodeMeter**.

For the updating of **dongles.4d**, see [9.4.1 Updating dongles.4d on page 69](#).

For the updating of **nodes.4d**, see [9.4.2 Updating nodes.4d on page 77](#).

### 9.4.1 Updating dongles.4d

The **dongles.4d** file lists the computers to search for 12d Network CodeMeters, 12d Local CodeMeters and Wibu dongles to find **12d dongle numbers**.

It also defines **the order to search for CodeMeters and Wibus**.

When **12d Model** is installed on a computer, it installs a **dongles.4d** file that is configured to only look for *Local (standalone) CodeMeters* and *Local Wibus*.

For each computer that needs to access to a **12d Network CodeMeter**, a modification has to be made to the **dongles.4d** file used by that computer to tell **12d Model** to **search for a 12d Network CodeMeter** and not just use a *12d Local CodeMeter*.

The updated **dongles.4d** is then placed in the standard search path for a set up file for that computer and the particular version of **12d Model**. For example, for **12d Model 15**, the **dongles.4d** could be in c:\12d\15.00\User. Or it uses a file pointed to by the environment variable **DONGLES\_4D** in **env.4d**. This means that the **dongles.4d** file could be on the one central computer and accessed by all the other computers.

#### Important Note

In the initial **12d Model** installation, the **dongles.4d** file is a set up file and is installed in the **Set\_ups** folder under the **12d Model** version number.


For example, for **12d Model 15**

**Program files\12d\12dmodel\15.00\Set\_ups**

All the files in *Set\_ups* are supplied by **12d Solutions** and must not be modified. Hence in updating the default **dongles.4d** file, the procedures outlined will modify a copy of the **dongles.4d** file.

The editing of **dongles.4d** **does not** have to be on the computer that the *12d Network CodeMeter* is on. It can be done from any computer.

To edit the **dongles.4d** file you need to start up **12d Model** BUT you don't have to open a **12d Model** project. The current **dongles.4d** file can be edited by simply starting up **12d Model** and clicking on the **dongles.4d** button on the front panel.




Or if the **12d Model** you are running is already authorized and you are in an open project, by picking the option

**Projects =>Management =>Dongles =>Dongles.4d editor**


Both of these bring up the **Dongles.4d Editor** panel.

If the **dongles.4d** is the one installed with **12d Model** then it will only be looking for **Local** (standalone) **CodeMeters** and Local (standalone) **Wibus**:



What it needs in the list is an entry to tell **12d Model** to look for **your 12d Network CodeMeter**.

To **Add** a new entry to dongles.4d, click on the **Add** button which then bring up the **Add a New Dongle** panel.




To add an entry to search for all Network CodeMeter on the network, see [9.4.1.1 Search for any 12d Network CodeMeter on page 71](#).

To add an entry to use a particular 12d dongle number in a particular 12d Network CodeMeter, see [9.4.1.2 Using a 12d Dongle Number in a 12d Network CodeMeter on page 74](#).


#### 9.4.1.1 Search for any 12d Network CodeMeter

The simplest entry to add is the one that searches for all 12d Network CodeMeters on the network.



For this case, select **CodeMeter - auto network** for **Type** and then click on **Add**.


A new entry with the default name **New dongle** is added to the bottom of the list.



Click in the **Name** field and change **New dongle** to whatever you want, say **CodeMeter - auto network**.

The order in the list is the order that **12d Model** searches to find a valid dongle.


For example if you want to always search for a **local dongle BEFORE the 12d Network CodeMeter** then leave the order as it is.




This is what is normally wanted. That is, use a local dongle if it exists, otherwise use a network license.

If you want to always search for a **12d Network CodeMeter BEFORE a local dongle** then use the Up arrow icon to move the **CodeMeter - auto network** to the top of the list. This is rarely wanted.





To save the information to the **dongles.4d** file, press **Write** to bring up the **Write Setup File "dongles.4d"** panel.



Tick on **User folder** and then on **Write**.

For any computer wanting to use a **12d Model** license from a 12d Network CodeMeter, the updated **dongles.4d** must be placed in the standard search path for the **User** folder, or in the folder pointed to by the environment variable **USER\_4D** in **env.4d**, or is the file pointed to by the environment variable **DONGLES\_4D** in **env.4d**.

Using **DONGLES\_4D** means that the **dongles.4d** file could be on a central computer that can be accessed by all the other Client computers.

**Note:**

If you don't want to search for a Local dongle at all. simply highlight the **Local** entries and click on the delete icon to delete them.

**WARNING**

Projects can have a local **dongles.4d** file and when the project is selected, the local **dongles.4d** is used before any other **dongles.4d**. If the local file does not have the correct network information in it then the authorization will fail because **12d Model** is no longer being instructed to use the Network CodeMeter.


### 9.4.1.2 Using a 12d Dongle Number in a 12d Network CodeMeter

To point to a particular **12d dongle number**, it helps to know the **physical** CodeMeter number that the **12d dongle number** is in.


If you don't already know this, the CodeMeter WebAdmin panel can be used to look inside the Network CodeMeter. See [Step 5. Checking the Virtual 12d Virtual Dongles Inside the Network CodeMeter on page 64](#).

**Note:** if you still don't know what Network CodeMeter the 12d dongle is in, it is possible to find it when using the **Dongles.4d Editor** but you will need to look through the list of physical CodeMeter numbers and see which one contains the required 12d dongle number.

In the **Add a New Dongle** panel, for the case of using a particular 12d dongle number, select **CodeMeter - network** for **Type** and then click on **Add**.




A new entry with the default name **New dongle** is added to the bottom of the list.



Click in the **Name** field and change **New dongle** to whatever you want but it helps to have the 12d dongle number in the name. For example **CodeMeter - ec51470022**

Next click on the **CodeMeter** icon at the end of the **Server name** field.

This will bring up the **CodeMeter Browse** panel that searches for all the 12d Network CodeMeters on the network and for all the **12d dongle numbers** in them, and presents the results in a tree.



Scroll down the tree until you find the **12d dongle number** you are after and click on it.

This will then write what is called the **CMUNC** to the **Server name** field.

**Aside:**


CMUNC is the 12d CodeMeter Universal Naming Convention. An example would be

```
//server_name.12d.com/2-2310242/1/16
```

where **server\_name** is the server name (Fred) with .12d.com added to it, followed by CodeMeter serial number (2-2310242), then the product code (1), and the final part being the instance within that product code that contains the 12d dongle number.

**Note:** The instance can only be found by using the **CodeMeter Browse** panel.

To save the information to the **dongles.4d** file, press **Write** to bring up the **Write Setup File "dongles.4d"** panel.



Tick on **User folder** and then on **Write**.

For any computer wanting to use a **12d Model** license from a 12d Network CodeMeter, the updated **dongles.4d** must be placed in the standard search path for the **User** folder, or in the folder pointed to by the environment variable **USER\_4D** in **env.4d**, or is the file pointed to by the environment variable **DONGLES\_4D** in **env.4d**.

Using **DONGLES\_4D** means that the **dongles.4d** file could be on a central computer that can be accessed by all the other Client computers.

#### WARNING

Projects can have a local *dongles.4d* file and when the project is selected, the local *dongles.4d* is used before any other *dongles.4d*. If the local file does not have the correct network information in it then the authorization will fail because **12d Model** is no longer being instructed to use the 12d Network CodeMeter.

For the updating of **nodes.4d**, see [9.4.1 Updating dongles.4d on page 69](#).

## 9.4.2 Updating nodes.4d


**12d Model** will not create new projects or open an existing project without an authorization file called **nodes.4d** with valid information in it.

The information inside **nodes.4d** controls

- (a) **which 12d dongles** are authorized to run **12d Model**
- (b) what **version** of **12d Model** will run for a 12d dongle
- (c) what **modules** are authorized for a particular 12d dongle


To authorize **12d Model** to run with **your 12d dongles**, a file called **nodes.12dxxn** where **xx** is the **12d Model** version number, will have been emailed to you by your local **12d Model** Reseller.

For example, for **12d Model 15** the file will be called **nodes.12d15n**




Installing **12d Model** on a computer sets up a *Windows* file association so that a **nodes.12dxxn** file is recognised brings up the **Install a 12d Model xx Nodes File** panel which is used to install a **nodes.4d** file in the correct location.

In the email, double click on the files **nodes.12dxxn** and the **Opening Mail Attachment** panel comes up.



Click on **Open** and then the **Install a 12d Model xx Nodes File** panel appears.



The choices for **Operation** are:


**Prepend** - if a **nodes.4d** file already exists, the information in the **nodes.12dxxn** file is added to the beginning of the existing **nodes.4d** file. A backup up copy of the existing **nodes.4d** is created **THIS IS THE NORMAL CHOICE**.

**Replace** - if a **nodes.4d** file already exists, it is replaced by a new **nodes.4d** file with the information in the **nodes.12dxxn** file in it. A backup up copy of the existing **nodes.4d** is created.

**Append** - if a **nodes.4d** file already exists, the information in the **nodes.12dxxn** file is added to the end of the existing **nodes.4d** file. A backup up copy of the existing **nodes.4d** is created. **THIS IS RARE**.

Select **Prepend**, **Replace** or **Append** and then click **Install**.

The new/updated **nodes.4d** file is created in the **Destination** folder (default is **C:\12d\15.00**) and if a **nodes.4d** file already existed, a backup copy of it is made.



**Note** - if you don't have the file **nodes.12dxxn** attached to an email but instead have the file in a folder accessible from your computer, then you can do the following:

If there is a **nodes.12dxxn** file, double click on that file and the **Install a 12d Model Nodes File** panel should appear and you continue with the instructions above.

If that doesn't work, start up **12d Model xx** and click on the **Nodes.4d** button at the bottom of the **Open a Recent Project** panel. This will also bring up the **Install a 12d Model Nodes File** panel and you can browse for the **nodes.12dxxn** file in the **Source** panel field. You can then continue with the instructions above.

For any computer wanting to use a **12d Model** license from a 12d Network CodeMeter, the updated **nodes.4d** is then placed in the standard search path for the **User** folder.

For example, for **12d Model 15** a **nodes.4d** in c:\12d\15.00, or a file pointed to by the environment variable **AUTHORIZATION\_4D** in **env.4d**.

Using **AUTHORIZATION\_4D** means that the **nodes.4d** file can be on a central computer and accessed by all the other Client computers.

Now that the **dongles.4d** file and the **nodes.4d** file have been updated, any computer on the network that has the CodeMeter drivers installed and has the updated **dongles.4d** and **nodes.4d** file should be able to obtain a **12d Model** license from a Network CodeMeter. That is, it becomes a **12d CodeMeter Client**.



This ends the notes for setting up the **12d CodeMeter Server** and any **12d CodeMeter Clients**.

## 10 CodeMeter Control Center & WebAdmin

The **CodeMeter Control Center** is used on a particular computer to display which CodeMeters are on the computer the Control Centre is being run on, to stop and start the **CodeMeter Runtime Server** service on the computer, Certify CodeMeters on the computer and to update the contents of any CodeMeters on the computer. It can also bring up the **CodeMeter WebAdmin** panel.

The **CodeMeter WebAdmin** can do whatever the Control Centre can do but it can work on CodeMeters on **ANY** computer that are visible on the network and it has permission to access.

To bring up the **CodeMeter Control Center**, click on the **CodeMeter** icon that was installed on your task bar.



Options under the **Process** menu can start and stop the **CodeMeter Runtime Server** service on the computer. See [10.1 Stopping & Starting the CodeMeter Runtime Server on page 81](#))

The **License Update** button is for reporting on, and updating the information about **12d Model** licenses for any CodeMeter (Network or Standalone) attached to **this** computer. See [10.5 Updating Licenses in Network CodeMeters on page 112](#)).

The **WebAdmin** button brings up the **CodeMeter WebAdmin** panel which can display information about **12d Model** licenses for **any** CodeMeter (Network or Standalone) that is visible on the computer network. See [10.8 Which Version of WebAdmin? on page 121](#).



## 10.1 Stopping & Starting the CodeMeter Runtime Server

Some changes to CodeMeter configurations on a computer require that the **CodeMeter Runtime Server** service is restarted on the computer. In these cases, there is usually a message to say **Changes only take effect after restarting CodeMeter**.

The stopping and starting of the CodeMeter Runtime Server on a particular computer can be done from running **CodeMeter Control Center** on that computer, or **WebAdmin** can be used to stop and start the CodeMeter Runtime Server on any computer that has access to and adequate permissions.

See

[10.1.1 CodeMeter Runtime Server - Control Centre on page 82](#)

[10.1.2 CodeMeter Runtime Server - WebAdmin on page 85](#)

## 10.1.1 CodeMeter Runtime Server - Control Centre


Click on the **CodeMeter** icon that was installed on your task bar to bring up the **CodeMeter Control Center**.



Clicking on the **WebAdmin** button on the **CodeMeter Control Center** brings up the **CodeMeter WebAdmin**.


**For WebAdmin 6:**

To **stop** the **CodeMeter Runtime Server** service, click on **Process > Stop CodeMeter Service** in the **CodeMeter Control Center**.




You will be asked to confirm that this is to be done.

The **CodeMeter Control Center** will then reappear with no CodeMeters being found on the computer and if you look in the Windows Task Manager, the **CodeMeter Runtime Server** service will be shown as **Stopped**.




To **start** the **CodeMeter Runtime Server** service, click on **Process > Start CodeMeter Service** in the **CodeMeter Control Center**.




You will be again be asked to confirm that it is to be done.


After a short time, the **CodeMeter Control Center** panel will then reappear displaying the CodeMeters on this computer.



If you look in the Windows Task Manager, the **CodeMeter Runtime Server** service will be shown as **Running**.



**Note:** There may be more than one **CodeMeter** attached to the computer. For example



**Warning:** Access to **all** the CodeMeters on the computer is stopped by stopping the **CodeMeter Runtime Server** service.


## 10.1.2 CodeMeter Runtime Server - WebAdmin

To bring up the **CodeMeter WebAdmin** panel, click on the **WebAdmin** button on the **CodeMeter Control Center**.


### For WebAdmin 6:

For instructions on how to select and see CodeMeters on a particular Network Server, see [10.4.1 Getting Info on CodeMeters on a Particular Server - WebAdmin 6 on page 99](#)


Once the required Computer is selected in the **CodeMeter WebAdmin** panel, to **stop** the Network Server, click on the **Configuration >Server >Server access** menu, then select **Disable** and finally click on **Apply**.



The **CodeMeter Control Center** will then reappear with no CodeMeters being found on the computer and if you look in the Windows Task Manager, the **CodeMeter Runtime Server** service will be shown as **Stopped**.




To **start** the **CodeMeter Runtime Server** service, click on the **Configuration >Server >Server access** menu, then select **Enable** and finally click on **Apply**



You will be again be asked to confirm that it is to be done.

If you look in the Windows Task Manager, the **CodeMeter Runtime Server** service will be shown as **Running**.



**Warning:** Access to **all** the CodeMeters on the computer is stopped by stopping the **CodeMeter Runtime Server** Service.

## 10.2 Port Address for CodeMeter Communication

For **CodeMeter WebAdmin 6**, see [10.2.1 Port Address - WebAdmin 6 on page 87](#)

For **CodeMeter WebAdmin 5**, see [10.2.2 Port Address - WebAdmin 5 on page 88](#).

### 10.2.1 Port Address - WebAdmin 6

The **CodeMeter License Server** uses a specific IP port (defaulted on 22350) to communicate with your computer and the network. This network port is registered at **IANA** (Internet Assigned Numbers Authority) and is uniquely assigned for CodeMeter® communication.

Please make sure that your firewall is not blocking this port.

Enable the used **IP port 22350** and make sure it is accessible by CodeMeter®, *i.e.* share the communication for this IP port.

The IP port used for communication can be changed by the **CodeMeter WebAdmin** panel.

Click on the **Configuration >Server >Server access** menu.

The screenshot shows the CodeMeter WebAdmin interface. The browser address bar indicates the URL is localhost:22350/configuration/server\_access.html. The navigation menu includes Dashboard, Container, License Monitoring, Diagnosis, Configuration, and Info. The Configuration menu is expanded, showing Basic, Server, and Advanced options. The Server option is selected, leading to the Server Access configuration page. The Network Server section is active, showing the 'Network Port \*' field set to 22350. The CmWAN Server section is also visible, with its port set to 22351. The 'Apply' and 'Restore Defaults' buttons are at the bottom. A note at the bottom states: (\*). Changes only take effect after restarting CodeMeter.

Change the **Network Port**: field to the number of the port that you want the CodeMeter to communicate over, and then press **Apply**.

**Important:** For the change to take effect, you need to stop and then restart the **CodeMeter Runtime Server** service. See [10.1 Stopping & Starting the CodeMeter Runtime Server on page 81](#).

## 10.2.2 Port Address - WebAdmin 5

The **CodeMeter License Server** uses a specific IP port (defaulted on 22350) to communicate with your computer and the network. This network port is registered at **IANA** (Internet Assigned Numbers Authority) and is uniquely assigned for CodeMeter® communication.

Please make sure that your firewall is not blocking this port.

Enable the used IP port 22350 and make sure it is accessible by CodeMeter®, *i.e.* share the communication for this IP port.

The IP port used for communication can be changed by the **CodeMeter WebAdmin** panel.

Click on the **Configuration >Server** tab.



The screenshot shows the CodeMeter WebAdmin interface. The main title is "CodeMeter WebAdmin" with a logo on the right. The navigation bar includes "Home", "Content", "Server", "Configuration", "Diagnosis", "Info", and "Help". The "Configuration" tab is selected, and the "Server" sub-tab is active. The "Network Port \*" field is set to 22350 and is circled in red. The "Run Network Server" checkbox is checked. The "Apply" and "Default" buttons are visible at the bottom.

Change the **Network Port**: field to the number of the port that you want the CodeMeter to communicate over, and then press **Apply**.

**Important:** For the change to take effect, you need to stop and then restart the **CodeMeter Runtime Server** service. See [10.1 Stopping & Starting the CodeMeter Runtime Server on page 81](#).



## 10.3 Certifying CodeMeters

Updating the **Certified Time** in a **CodeMeter** must be done at least every two month over the Internet and Certifying needs communication between the **CodeMeter** and a **Certified Wibu Time Server**.

So for Certification to occur, a computer that can access the **CodeMeter** must also **have access to the Internet at least every two months** so it can run the Certification.

Certifying a CodeMeter can be done

- (a) manually from inside **12d Model** itself

See [5.1 Certifying CodeMeters from 12d Model on page 30](#)

- (b) automatically by **12d Model**

See [5.2 Automatically Certifying CodeMeters from 12d Model on page 32](#)

- (c) outside of **12d Model** when the CodeMeter is on the computer you are using outside

Using the **CodeMeter Control Centre** - see [5.3 Certifying CodeMeters Using Control Center on page 33](#).

or

- (d) outside **12d Model** when the CodeMeter is **NOT** on the computer your are using

It is possible to certify CodeMeters that are on other computers but this is usually only needed by Administrators. See [10.3.1 Certifying CodeMeters Using WebAdmin on page 90](#)


### Important Note

To display and update the **Certified Time** in the **CodeMeter**, you need access over the Internet to a **CodeMeter Time Server** (see [10.3.2 Time Servers for Certified Time on page 96](#)) and this Internet communication must be allowed to be done through an **IP port** (see [9 Network CodeMeters on page 55](#)).

Please contact your **12d Model Reseller** if you are having problems certifying your **CodeMeter**.

## 10.3.1 Certifying CodeMeters Using WebAdmin

If the **CodeMeter** is **NOT** attached to your current computer you need to use the **CodeMeter WebAdmin** panel which is brought up by clicking on the **WebAdmin** button on the **CodeMeter Control Center**.



For **CodeMeter WebAdmin 6**, see [10.3.1.1 Certifying CodeMeters Using WebAdmin 6 on page 91](#)

For **CodeMeter WebAdmin 5**, see [10.3.1.2 Certifying CodeMeters Using WebAdmin 5 on page 95](#).

### 10.3.1.1 Certifying CodeMeters Using WebAdmin 6

After getting up CodeMeter WebAdmin panel up, on the **Dashboard** you need to set the **Current Server** to the server that the CodeMeter is on.


To get a list of servers, click on the Current Server: field at the bottom of the Dashboard and you will get a list of the servers found.



The screenshot shows the CodeMeter WebAdmin Dashboard in a browser window. The browser address bar shows `localhost:22350/index.html`. The dashboard header includes the WJBU SYSTEMS logo and the title "CodeMeter WebAdmin". The navigation menu includes "Dashboard", "Container", "License Monitoring", "Diagnosis", "Configuration", and "Info". The main content area displays the following server information:


Current Server:	RanchDocco
IP-Address:	.151
Operating System:	Microsoft Windows 10 Enterprise, 64-Bit
Server Startup:	2018-11-18 05:35:43
Server Version:	Version 6.30a of Jul/28/2016 (Build 2266)
Runtime Version:	6.30a

At the bottom of the dashboard, a teal bar displays "Current Server: localhost (127.0.0.1)" with a red circle around it, and "WebAdmin Version: 6.30" to the right.




If there is more than one **CodeMeter** on that computer/server, select the one that you want to examine and click on **Apply**.

The information about the selected Server will be displayed, including any CodeMeters that are found on the server and the current sessions on them.




If there is more than one **CodeMeter (CmContainer)** on that computer/server, select the one that you want by Walking right on the **Container** menu.




Information about the selected CodeMeter is then displayed.

Click on the **CmContainer Info** button to expand the information displayed.



The current **Certified time** for that **CodeMeter** will be displayed.

The **Certified time** for that **CodeMeter** can be updated to the current date by clicking on the **Update** button.



If you have permission to do so, the **Certified time** for that **CodeMeter** can be updated to the current date by clicking on the **Update** button.

Please contact your **12d Model Reseller** if you are having problems certifying your **CodeMeter**.

### Important Note

To display and update the **Certified Time** in the **CodeMeter**, you need access over the Internet to a **CodeMeter Time Server** (see [10.3.2 Time Servers for Certified Time on page 96](#)). This Internet communication is through a set IP port (see [9 Network CodeMeters on page 55](#)).

### 10.3.1.2 Certifying CodeMeters Using WebAdmin 5

After getting up CodeMeter WebAdmin panel up, on the **Home** tab set the **Host Name:** field to the name of the computer or server that the **CodeMeter** to be certified is on, and then go to the **Content >CmContainer** tab.

The screenshot shows the CodeMeter WebAdmin interface. The top navigation bar includes 'Home', 'Content', 'Server', 'Configuration', 'Diagnosis', 'Info', and 'Help'. The 'Content' tab is selected, and the 'CmContainer' sub-tab is also selected. Below the navigation bar, there are links for 'Licenses', 'User Data', and 'Backup/Restore'. The main content area displays the configuration for a specific CmContainer. The 'CmContainer:' field is set to '2-2310278'. The 'Name:' field is empty. The 'CmContainer Type:' is 'CmStick 2.04'. The 'First Device:' is 'No drive assigned (HID)'. The 'Status:' is 'Disabled'. The 'System Time (PC):' is '2015-09-03 17:40:47'. The 'System Time (CmContainer):' is '2015-09-03 17:40:47'. The 'Certified Time (CmContainer):' is '2015-09-03 17:13:38' and is circled in red. The 'Free Memory:' is '93 % (367.432 Bytes)'. There is an 'Update' button circled in red and a 'Defragment' button. Callouts with arrows point to the 'Certified time' field and the 'Update' button, with text 'click to update the Certified time'.

If there is more than one **CodeMeter (CmContainer)** on that computer/server, select the one that you want to examine in the **CmContainer:** field.

The **Certified time** for that **CodeMeter** can be updated to the current date by clicking on the **Update** button.

Please contact your **12d Model Reseller** if you are having problems certifying your **CodeMeter**.

#### Important Note

To display and update the **Certified Time** in the **CodeMeter**, you need access over the Internet to a **CodeMeter Time Server** (see [10.3.2 Time Servers for Certified Time on page 96](#)). This Internet communication is through a set IP port (see [9 Network CodeMeters on page 55](#)).

## 10.3.2 Time Servers for Certified Time


When you certify a **CodeMeter** it searches the internet for a **CodeMeter Time Server** to update the **Certified Time** in the CodeMeter.

For **CodeMeter WebAdmin 6**, see [10.3.2.1 Time Servers - WebAdmin 6 on page 96](#)


For **CodeMeter WebAdmin 5**, see [10.3.2.2 Time Servers - WebAdmin 5 on page 97](#).

### 10.3.2.1 Time Servers - WebAdmin 6

For a particular **CodeMeter** on a Server, the Internet or IP addresses of the **CodeMeter Time Servers** that are searched to set the **Certified Time** are given in the **Configuration > Certified Time** tab of the **CodeMeter WebAdmin** panel.



The list of **Time Servers** used for **this** CodeMeter are then displayed.



The Time Servers list is searched in order from the top to the bottom.



Servers in the list are added or removed using the **add** or **remove** buttons, and a highlighted entry in the list is moved up or down with the **up** and **down** buttons.

Clicking **Apply** saves these entries in the Windows Registry of the Server that the CodeMeter is on.

### 10.3.2.2 Time Servers - WebAdmin 5

For a particular **CodeMeter** on a Server, the Internet or IP addresses of the CodeMeter Time Servers that are searched to set the **Certified Time** are given in the **Configuration > Certified Time** tab of the **CodeMeter WebAdmin** panel.

The screenshot shows the CodeMeter WebAdmin interface. The top navigation bar includes 'Home', 'Content', 'Server', 'Configuration', 'Diagnosis', 'Info', and 'Help'. The 'Configuration' tab is selected and highlighted with a red box. Below the navigation bar, the 'Certified Time' tab is also highlighted with a red box. The main content area is titled 'Certified Time' and contains a list of time servers under the label 'Time Server:'. The list includes: cmtime.codemeter.com, cmtime.codemeter.us, cmtime.codemeter.fr, and cmtime.codemeter.de. This list is enclosed in a red rounded rectangle. Below the list are four buttons: 'add', 'remove', 'up', and 'down'. Below these buttons is a 'Time Out:' field with a text input containing '20' and a 'sec' label. At the bottom of the form are two buttons: 'Apply' and 'Default'.

The Time Servers to search are given in the list labelled **Time Server:** and the list is searched in order from the top to the bottom.

The Timer Servers can be specified by either an Internet address or an IP address.

Servers in the list are added or removed using the **add** or **remove** buttons, and a highlighted entry in the list is moved up or down with the **up** and **down** buttons.

Clicking **Apply** saves these entries in the Windows Registry of the Server that the CodeMeter is on.

## 10.4 Monitoring and Cancelling Licenses

Clicking on the **WebAdmin** button brings up the **CodeMeter WebAdmin** panel which can display information about **12d Model** licenses for **any** CodeMeter (Network or Standalone) that is visible on the computer network.

For instructions on finding information about **CodeMeters** on a **particular Network Server**, see

[10.4.1 Getting Info on CodeMeters on a Particular Server - WebAdmin 6 on page 99](#)

[10.4.3 Getting Info on CodeMeters on a Particular Server - WebAdmin 5 on page 106.](#)


### 10.4.1 Getting Info on CodeMeters on a Particular Server - WebAdmin 6


Clicking on the **WebAdmin** button brings up the **CodeMeter WebAdmin** panel which can display information about **12d Model** licenses for **any** CodeMeter (Network or Standalone) that is visible on the computer network.

The panel comes up with the **Dashboard** tab displaying information about one of the CodeMeters on **this** computer.

To get information about CodeMeters on another Server, you need to set the **Current Server** to the server that you wish to exam **CodeMeters** on.

To get a list of servers, click on the Current Server: field at the bottom of the Dashboard:





**Important Note:**

It is possible to have different versions of **WebAdmin** installed on different Servers. So depending on which Server you are looking at, you may now need to swap between the notes for **WebAdmin 6** and **WebAdmin 5**.

For instructions on Monitoring and Cancelling Licenses on this **Server**, see [10.4.2 Monitoring and Cancelling Licenses - WebAdmin 6 on page 101](#) [10.4.4 Monitoring and Cancelling Licenses - WebAdmin 5 on page 108](#).

## 10.4.2 Monitoring and Cancelling Licenses - WebAdmin 6

The information about a selected Server will be displayed, including any CodeMeters that are found on the server and the current sessions on them.

The screenshot shows the CodeMeter WebAdmin dashboard. The left sidebar contains navigation options: Dashboard, Container, License Monitoring, Diagnosis, Configuration, and Info. The main content area is divided into two sections. The left section displays server details for 'SERVER' with IP address '.252', running 'Microsoft Windows Server 2012 R2 Standard, 64-Bit', started on '2018-10-15 16:28:48', version '6.40a of Dec/22/2016 (Build 2402)', and runtime version '6.40a'. The right section, titled 'Sessions (2)', is highlighted with a red box and contains a table of active sessions:

Host	Product Code	Product Name
docco.12d.com	101956 : 1	12d Model - Stock - 12d Solutions - e c51470113
docco.12d.com	101956 : 1	12d Model - Stock - 12d Solutions - e c51470113

To find out information about all the **CodeMeters (CmContainer)** on that computer/server, select the **Container >All Containers** option, and expand the **12d Model** product code **101956** for each CodeMeter to show any **virtual 12d dongles** in a CodeMeter or any **standalone** CodeMeters.

The example below shows a Server with three CodeMeters attached to it: one with a single virtual 12d dongle, one with two virtual 12d dongles and one which is a standalone CodeMeter.

The screenshot displays the WebAdmin interface for License Monitoring. It shows three CodeMeter instances, each with a table of licenses. Annotations highlight specific details:

- CodeMeter 1 (2-2310233):** Labeled "CodeMeter numbers". It contains two licenses for product code 101956, annotated as "two virtual 12d dongles in the one CodeMeter".
- CodeMeter 2 (2-2310242):** Labeled "one 12d Model virtual dongle in a CodeMeter". It contains one license for product code 101956.
- CodeMeter 3 (3-4025920):** Labeled "one standalone 12d Model CodeMeter". It contains one license for product code 101956.

The license table for the first CodeMeter (2-2310233) is as follows:

Product Code	Name	Unit Counter	Valid Until	License Quantity	Feature Map
1	12d Model - Stock - 12d Solutions - ec51470113	n/a	n/a	5	n/a
1	12d Model - Stock - 12d Solutions - ec51470114	n/a	n/a	25	n/a

The license table for the second CodeMeter (2-2310242) is as follows:


Product Code	Name	Unit Counter	Valid Until	License Quantity	Feature Map
1	12d Model - 12D Solutions - NSW - ec51470101	n/a	n/a	3	n/a

The license table for the third CodeMeter (3-4025920) is as follows:


Product Code	Name	Unit Counter	Valid Until	License Quantity	Feature Map
1	12d Model - 12d Solutions - 5c2d470ac1	n/a	n/a	1	n/a

At the bottom of the interface, it shows "Current Server: SERVER (252)" and "WebAdmin Version: 6.40".

If there is more than one **CodeMeter (CmContainer)** on the computer/server, information about just one of them can be obtained by walking right on the **Container >All Container** menu and selecting the required CodeMeter number.




Information about the selected CodeMeter is then displayed. Expanding the **12d Model product code 101956** will show any **virtual 12d dongles** in a CodeMeter.




And as discussed in the Certifying section, clicking on the **CmContainer Info** button expands the information displayed for the **CodeMeter**.

To see information about the total number of licenses available for each **virtual 12d dongle**, and the number of licenses currently being used and how many are left to use, click on the **License Monitoring >All Licenses** menu.



Information about the selected CodeMeter is then displayed.





CodeMeter WebAdmin

Dashboard Container License Monitoring Diagnosis Configuration Info

All Licenses English (US)

### Available Licenses on 'BUILD-SERVER'

Number of licenses free

one 12d Model virtual dongle in a CodeMeter

Number of licenses being used

two 12d Model virtual dongles in a CodeMeter

Number of licenses on each virtual 12d dongle

Product Code	Name	Feature Map	License Quantity	Used	Available
10	CodeMeter Test Firm Code				
100003					
100021	WIBU-SYSTEMS AG				
101956	12d.com				
1	12d Model - 12d Solutions - NSW - ec51470101	-	3	0	3
1	12d Model - Stock - 12d Solutions - ec51470113	-	5	2	3
1	12d Model - Stock - 12d Solutions - ec51470114	-	25	0	25
1	12d Model - 12d Solutions - 5c2d470ac1	-	1	0	1

Information last updated on 2018-12-25 11:29:20

Clicking on the Product Code 1 for a CodeMeter showing some licenses are being used will (for example ec514470113), displays the user name of the user of each license (session).

If you have the required permission, the session can be **terminated** by selecting **Cancel** at the end of the session row and in the **Action** column.

CodeMeter WebAdmin

Dashboard Container License Monitoring Diagnosis Configuration Info

All Licenses <no name> (2-2310233) - Entry 101956:1 (-) English (US)

### License Monitoring Details

user for the session

click to Cancel the session

CmContainer	Entry	Available	Total
<no name> (2-2310233)	101956:1 (-)	3	5

ID	Client (User)	Client Process ID	Application Information	Access Mode	First Access	Last Access	Expires	Action
213	.151 ( candice)	0		User Limit	2018-12-25 08:40:24	2018-12-26 12:10:56		
220	.151 ( candice)	0		User Limit	2018-12-25 08:39:53	2018-12-26 12:10:35		

Information last updated on 2018-12-26 12:11:17

Current Server: SERVER (.252) WebAdmin Version: 6.40

### 10.4.3 Getting Info on CodeMeters on a Particular Server - WebAdmin 5

Clicking on the **WebAdmin** button brings up the **CodeMeter WebAdmin** panel which can display information about **12d Model** licenses for **any** CodeMeter (Network or Standalone) that is visible on the computer network.


The panel comes up with the **Content > CmContainer** tab displaying information about one of the CodeMeters on **this** computer.

The screenshot shows the CodeMeter WebAdmin interface. At the top, there is a navigation bar with tabs: Home, Content, Server, Configuration, Diagnosis, Info, and Help. The 'Content' tab is selected, and a sub-tab 'CmContainer' is also selected. Below the navigation bar, there are links for Licenses, User Data, and Backup/Restore. The main content area displays the following information:

CmContainer:	2-2310278	<input type="button" value="v"/>
Name:	<no name>	
CmContainer Type:	CmStick 2.04	
First Device:	No drive assigned (HID)	
Status:	<input checked="" type="radio"/> Disabled <input type="radio"/> Enabled until Unplugged <input type="radio"/> Enabled	
System Time (PC):	2015-08-14 17:24:11	
System Time (CmContainer):	2015-08-14 17:24:10	
Certified Time (CmContainer):	2015-08-14 15:36:01	<input type="button" value="Update"/>
Free Memory:	93 % (367.432 Bytes)	<input type="button" value="Defragment"/>

CodeMeters on other computer can be examined by clicking on the **Home** tab and then clicking on the displayed **Host Name**: to bring up the panel to select a **Server** to check for CodeMeters.

A pop up list is automatically created of all the computers that are visible on the network and have CodeMeters on them.



Picking a Server/Computer from the list and then pressing **Select** will set the **Host Name:** to the selected computer and all the tabs on the **CodeMeter WebAdmin** panel will then show information about the CodeMeters on the selected computer.

**Important Note:**

It is possible to have different versions of **WebAdmin** installed on different Servers.

So depending on which Server you are looking at, you may now need to swap between the notes for **WebAdmin 6** and **WebAdmin 5**.

For instructions on Monitoring and Cancelling Licenses on this **Server**, see

[10.4.2 Monitoring and Cancelling Licenses - WebAdmin 6 on page 101](#)

[10.4.4 Monitoring and Cancelling Licenses - WebAdmin 5 on page 108.](#)

## 10.4.4 Monitoring and Cancelling Licenses - WebAdmin 5

The tab **Content >Licenses** will display information about any selected CodeMeter on the selected computer.

The screenshot shows the CodeMeter WebAdmin interface. The 'Content' tab is selected, and the 'Licenses' sub-tab is active. The 'CmContainer' is set to '2-2310233'. The interface displays two tables of licensing information:

100003   Bundling Articles					
Product Code	Name	Unit Counter	Expiration Time	Activation Time	License Quantity
<a href="#">1</a>	SecuriKey Lite	n/a	n/a	n/a	1

101956   12d.com					
Product Code	Name	Unit Counter	Expiration Time	Activation Time	License Quantity
<a href="#">1</a>	12d Model - Stock - 12d Solutions - ec51470113	n/a	n/a	n/a	5
<a href="#">1</a>	12d Model - Stock - 12d Solutions - ec51470114	n/a	n/a	n/a	25

To see how many **12d Model** licenses are being used by each virtual **12d dongle** in all the CodeMeters on a particular Server, when that server has been selected on the **Home** tab, click on the **Server >User** tab.

**CodeMeter WebAdmin**

Home Content **Server** Configuration Diagnosis Info Help

Cluster | User

Available Network Licenses at 'BUILD-SERVER'

Product Code	Name	Feature Map	Licenses	Status					
				User Limit (Borrowed)	No User Limit	Exclusive	Shared	Free	
<b>10   CodeMeter Test Firm Code</b>									
13	Test Entry	-	1	0 (-)	0	0	0	1	<a href="#">Details</a>
1608	CmDemo for C++ created this Product Item	-	1	0 (-)	0	0	0	1	<a href="#">Details</a>
<b>101956   12d.com</b>									
1	12d Model - 12D Solutions - NSW - ec51470101	-	3	0 (-)	0	0	0	3	<a href="#">Details</a>
1	12d Model - Stock - 12d Solutions - ec51470113	-	5	2 (-)	0	0	0	3	<a href="#">Details</a>
1	12d Model - Stock - 12d Solutions - ec51470114	-	25	0 (-)	0	0	0	25	<a href="#">Details</a>

Information last updated on Aug/14/2015 19:47:58

The **12d dongles** are displayed under the section titled **101956 | 12d.com**.

The table also displays how many **12d Model licenses** are on each **12d dongles**, and how many of those licenses are still **Free** to be used.

Details about each user on a particular **12d dongle** is displayed by clicking on the **Details** button at the end of the row for that virtual **12d dongle**.

**CodeMeter WebAdmin**

Home Content Server Configuration Diagnosis Info Help

Cluster | User


**License Details CmContainer 2-2310233**

Entry 101956 : 1 (-)  
 Free 3  
 Total 5

ID	Client (User)	Client Process ID	Application Information	Access Mode	First Access	Last Access	Expires	Action
229	.117 (T3600-1 \ alg)	0		User Limit	2015-08-14 19:41:48	2015-08-14 19:49:22		Cancel
242	.117 (T3600-1 \ alg)	0		User Limit	2015-08-14 19:41:57	2015-08-14 19:48:15		Cancel

Information last updated on Aug/14/2015 19:49:25

A particular user session of **12d Model** can be stopped by clicking on the **Cancel** button. A **Confirmation** panel will then be brought up.



If you click on **OK** and have permission to be able to stop people, the session will be terminated. If you do not have permission, you will get the message



## 10.5 Updating Licenses in Network CodeMeters

A **Network CodeMeter** can contain one or more **virtual 12d dongles** and each of these virtual dongles can have a different number of **12d Model** licenses.

Adding extra **12d dongles**, or modifying the number of licenses on each of the **12d dongles** can be done electronically without having to remove the Network CodeMeter from the computer.

Updating virtual **12d dongles** is usually one simple step but it may involve two steps.

### Step 1. Generating the CodeMeter Context File (.WibuCmRaC) - only if asked for

The *context* (.WibuCmRaC) file holds information about the current settings in the Network CodeMeter. **12d Solutions** usually knows these setting for your Network CodeMeter and this step is normally not required.

However sometimes you may be asked to generate the .WibuCmRaC file and email it to your local **12d Model** Distributor.

If you need to generate the **.WibuCmRaC** file, go to [10.5.1 Generating the Context File \(.WibuCmRac\) on page 113.](#)

### Step 2. Updating the Network CodeMeter with the .WibuCmRaU file

You will be emailed one or more special files (ending in **.WibuCmRaU**) which are used to update the information about the virtual **12d dongles** in the Network CodeMeter.



If you have a **WibuCmRaU** file, go to [10.5.1.1 Updating Using the .WibuCmRaU File on page 116.](#)



## 10.5.1 Generating the Context File (.WibuCmRac)

The follow steps will generate a new context file for a Network CodeMeter using the *CodeMeter Control Center* panel.


The *CodeMeter Control Center* panel is accessed by clicking on the **CodeMeter** icon that was installed on your task bar.




Click on **License Update** to bring up the **CmFAS Assistant** panel.




Select **Next**.



Tick on **Create receipt** and then select **Next**.



Tick on **12d.com** and then select **Next**.



Select the file to use to update the CodeMeter and then select **Commit**.

Email the **.WibuCmRaC** file to your **12d Model Reseller**.

Your **12d Model Reseller** will then be able to send you a **.WibuCmRaU** file to update your Network CodeMeter.

For information on how to use a **.WibuCmRaU** file to update the CodeMeter, see [10.5.1.1 Updating Using the .WibuCmRaU File on page 116](#).

### 10.5.1.1 Updating Using the .WibuCmRaU File

The number of virtual **12d dongles** and the number of **12d Model** licenses on them can be changed electronically without having to remove the CodeMeter from the computer.


To update the CodeMeter, you will be sent a file starting with the CodeMeter number, then the date and finally ending in **.WibuCmRau**.

The steps below will show how to use the **.WibuCmRau** file to update the Network CodeMeter


**You need to have System Administrator rights to update the Network CodeMeter.**

Before updating a Network CodeMeter dongle, run the **CodeMeter WebAdmin** software to check that no one is using the Network CodeMeter ([10.4 Monitoring and Cancelling Licenses on page 98](#)). The **CodeMeter WebAdmin** displays network dongle activity and it can also remove users from the network dongle.

Once all the users are off the Network CodeMeter, double click on the file **codemeter\_number\_date.WibuCmRau** and the following panel will appear:



Select **Yes** and a panel to say how many CodeMeters have been updated should appear.



The CodeMeter should now be updated. The **CodeMeter WebAdmin** can be used to check that the new number of licenses, or new number of 12d dongles, are now available.

**WARNING:** If there is **no** association for the **.WibuCmRau** file, double clicking on the **.WibuCmRau** file won't work. In that case go to [10.5.1.2 Manually Updating the Network CodeMeter on page 117](#).


#### Nodes.4d:

If you've added a new **virtual 12d dongle** to your CodeMeter then a new **nodes.4d** file with that 12d dongle number in it will be needed. If all you did was change the number of licenses for an **existing 12d dongle** in the Network CodeMeter then a new **nodes.4d** file is not required.

### 10.5.1.2 Manually Updating the Network CodeMeter

If there is **no association** with the **.WibuCmRau** file then double clicking on the **.WibuCmRau** file won't automatically run the CodeMeter update program. So instead, the update will have to be done manually using the *CodeMeter Control Center* panel.


The *CodeMeter Control Center* panel is accessed by clicking on the **CodeMeter** icon that was installed on your task bar.




Click on **License Update** to bring up the **CmFAS Assistant** panel.



Select **Next**.



Tick on **Import license update** and then **Next**.



Select the file to use to update the CodeMeter and then select on **Commit**.


#### **Nodes.4d:**

If you've added a new *virtual 12d dongle* to your CodeMeter then a new **nodes.4d** file with that 12d dongle number in it will be needed. If all you did was change the number of licenses for an **existing 12d dongle** in the Network CodeMeter then a new **nodes.4d** file is not required.

**Note** - if the CodeMeter that the file applies to is not on the computer then an **Error** message will be brought up. See [10.5.2 Errors Updating the Network CodeMeter on page 119](#).

## 10.5.2 Errors Updating the Network CodeMeter

If there was a problem, instead of the dialogue stating that the CodeMeter has been updated, a CodeMeter error panel will appear. For example:



If you can't work out what your error was, email the error message to your **12d Model Reseller**. Doing a *Print Screen* and saving the *png* or *bmp* is the best way to record details of the error and send the image to your **12d Model Reseller**.

## 10.6 Replacing an Existing Network CodeMeter

Before removing a Network CodeMeter, run the *CodeMeter WebAdmin* software to check that no one is using the Network CodeMeter dongle ([10.4 Monitoring and Cancelling Licenses on page 98](#)).

If there are no user on the Network CodeMeter, the existing Network CodeMeter can be removed from the computer and the new Network CodeMeter attached.

The new Network CodeMeter should now be ready to use.

**NOTE** - a new nodes file will be required for the new virtual **12d dongles** that are in the new Network CodeMeter.

## 10.7 End of the Notes on Network CodeMeters

This ends the general notes on the Network CodeMeter.

However information on Certifying Network CodeMeters is covered in [8 Errors Installing and Authorising on page 51](#).

If you need to install **12d Model** on a computer, go to the section [2 Installing 12d Model 15 Release Version on page 6](#).

The links for downloading documentation on **12d Model** are given in [6 Documentation on page 40](#).

The links for downloading information, power points and videos on what is new in **12d Model 15** are given in [7 What's New in 12d Model 15 on page 49](#).




## 10.8 Which Version of WebAdmin?

Clicking on the **WebAdmin** button brings up the **CodeMeter WebAdmin** panel which can display information about **12d Model** licenses for **any** CodeMeter (Network or Standalone) that is visible on Servers in the computer network.


Depending on when the **CodeMeter** was installed on a particular Server, you can get different versions of the **WebAdmin** pages.

If on a Server the **WebAdmin Dashboard** page looks like:



In this case you need to follow instructions and images for **CodeMeter WebAdmin 6**

Otherwise if the **WebAdmin Home** page on a Server looks like:



In this case you need to follow instructions and images for **CodeMeter WebAdmin 5**

### Important Note:

It is possible to have different versions of **WebAdmin** installed on different Servers.

So depending on which Server you are looking at, you may need to swap between the notes for **WebAdmin 6** and **WebAdmin 5**.

For instructions on finding information about **CodeMeters** on a **particular Network Server**, see

[10.4.1 Getting Info on CodeMeters on a Particular Server - WebAdmin 6 on page 99](#)

[10.4.3 Getting Info on CodeMeters on a Particular Server - WebAdmin 5 on page 106.](#)

